

Modelling of quantum networks

Anna B. Mikhailova* and Lev Prokhorov†

*Laboratory of Quantum Networks, V.A.Fock Institute for Physics
of St.Petersburg University, St.Petersburg 198504, Russia*

Boris S. Pavlov‡

*Department of Mathematics, University of Auckland,
Private Bag 92019, Auckland, New Zealand*

Abstract

Mathematical design of a quantum network with prescribed transport properties is equivalent to the Inverse Scattering Problem for Schrödinger equation on a composite domain consisting of quantum wells and finite or semi-infinite quantum wires attached to them. An alternative approach to study of transport properties of networks, based on solution of the direct Scattering problem, is also possible, but optimization of design requires scanning over the multi-dimensional space of essential physical and geometrical parameters of the network. We propose a quantitatively consistent description of one-particle transport in the network based on observation that the transmission of an electron across the wells, from one quantum wire to the other, happens due to the excitation of oscillatory modes in the well. This approach permits us to obtain an approximate formula for the transmission coefficients based on numerical data for eigenvalues and eigenfunctions of the discrete spectrum of some intermediate Schrödinger operator on the network in certain range of energy. The obtained approximate formula for the transmission coefficients permits to reduce the region of search in the space of parameters in course of optimization of the design. We interpret the corresponding approximate Scattering matrix as a Scattering matrix of the relevant solvable model which can be used when modelling the network by a quantum graph.

PACS numbers: 73.63.Hs, 73.23.Ad, 85.35.-p, 85.35.Be

Keywords: Quantum well, Scattering, Solvable model

*Electronic address: baltic@teia.org

†Electronic address: Lev.Prokhorov@pobox.spbu.ru

‡Electronic address: pavlov@math.auckland.ac.nz

I. INTRODUCTION

Modern interest to quantum networks is inspired by the engineering of quantum electronic devices and oriented to manufacturing of networks with prescribed transport properties. In simplest case of a single-particle, single-mode processes transport properties can be described in terms of Scattering. Quantum conductance was related to Scattering Processes in pioneering papers by Landauer and Büttiker, see [16, 58], and the role of the resonance scattering in mathematical design of quantum electronic devices was clearly understood by the beginning of the nineties, see [1, 12, 15]. Nevertheless practical design of devices up to now, see for instance [22], was based on the formal resonance of energy levels rather than on resonance properties of the corresponding wave functions. At the same time importance of interference in mathematical design of devices was noticed in [3, 27] and intensely studied in [28, 42, 45, 67], see also recent papers [85, 93, 94, 95].

Experimental technique already permits to observe resonance effects caused by the shape of the resonance wave functions, see [7, 8, 91]. In our previous papers, see for instance [9, 10, 11], we proposed using the shape resonance effects as a tool for manipulation of the quantum current. In particular, we considered the process of resonance transmission of an electron in the switch across the quantum well from one quantum wire to another based on excitation of resonance modes inside the vertex domain- a phenomenon which was first mathematically described in [32].

In actual paper we apply this basic idea to description of one-electron transmission in general quantum networks which can be formed on the surface of a semiconductor of quantum wells and quantum wires joining them or connecting them to infinity. The depth of the wires and the wells with respect to the potential on the complement of the network is assumed large enough to replace the matching boundary conditions on the boundary of the network by homogeneous Dirichlet conditions for electrons with energy close to the Fermi level $E_F = \Lambda$ in the wires, see [60]. The limitations we impose on the width δ of the wires are practically *not too strict*. They are defined from comparison of the non-dimensional wave-number of electron in the wires on Fermi level Λ and the non-dimensional inverse spacing between eigenvalues of an intermediate operator on the resonance level $\lambda \approx \Lambda$. The numerical analysis of the circular quantum switch, see [11], shows that our approximation is applicable to the network constructed of a circular vertex domain with diameter d and quantum wired width δ submitted to the condition $d \geq 4\delta$. Hence our further assumptions on the width of the wires do not mean actually that the wires are “thin” or the connection of the wires to the quantum wells is weak, though we include below, lemma 3.1, also analysis of this case. We assume that the dynamics of the electrons in the wires is single-mode and ballistic on large intervals of the wires compared with the size of geometric details of the construction (the width of the wire or the size of the contacts). Our methods in this paper are based on analysis of the one-body scattering problem for the relevant Schrödinger equation on the network.

A general Quantum network which is studied in this paper is a composite domain of a sophisticated form, a sort of a “fattened graph”, see for instance [55]. It is impossible to obtain an explicit solution of the Schrödinger equation on this domain in analytic form. On the other hand, the direct computation is not efficient for optimization of the construction of

the network with prescribed transport properties, because the resonance transmission effect is observed only at a multiple point in the space of geometrical and physical parameters.

Substitution of the network by proper one-dimensional graph with special boundary conditions at the vertices looks like an attractive program aimed to obtaining explicit formulae for solutions of the Schrödinger equation on the network, see [14, 33, 52, 66]. Really, analysis of the one-dimensional Schrödinger equation on the graph, or even on some hybrid domain as in [62, 63] is a comparatively simple mathematical alternative, but estimation of the error appearing from the substitution of the network by a corresponding graph is difficult. Asymptotic behavior of discrete spectrum in composite domains with shrinking channels was studied in [43] see also references therein. Simultaneous shrinking joining channels and vertex domains of a realistic compact network was studied in extended series of papers on the edge of last century. In particular in [55, 83] the authors develop, based on [86], a variational technique for discrete spectrum of Schrödinger operator on a “fattened graph”. They noticed that the (discrete) spectrum of the Laplacian on a system of *finite length* shrinking wave-guides, width ε , attached to the shrinking vertex domain diameter ε^α , $0 < \alpha < 1$ tends to the spectrum of the Laplacian on the corresponding one-dimensional graph but with different boundary conditions at vertices depending on speed of shrinking. In case of “small protrusion” $1/2 < \alpha < 1$ the spectrum in the corresponding composite domain tends to the spectrum on a graph with Kirchhoff boundary conditions at vertices; for the intermediate case $\alpha = 1/2$ the boundary condition becomes energy-dependent, and for “large protrusion”, $0 < \alpha < 1/2$, the spectrum on a system of wave-guides, when shrinking, tends to the spectrum on the graph with zero boundary conditions at the points of contact so the vertices play the role of “black holes” according to [55].

In distinction from the papers [55, 83] quoted above, our theoretical analysis of the Schrödinger equation on the “fattened graph” [69] was based on a *single-mode one-body scattering problem* in the corresponding composite domain with several semi-infinite wires. The aim of actual paper is: an “approximate” description of transport properties of the network. We achieve this aim via derivation of an explicit formula for the Scattering Matrix in terms of the Dirichlet-to-Neumann map of a specific *intermediate operator* obtained via proper splitting (see [35]) of the relevant Schrödinger operator \mathcal{L} on the whole network in a certain interval of energy. Construction of the system of intermediate operators $\{L_\Lambda\}$ is defined by the band structure of the absolutely continuous spectrum σ_a of the Schrödinger operator on the network the following way.

The multiplicity $n = n_\lambda$ of the absolutely continuous spectrum of the Schrödinger operator on the network is finite on each finite interval. If the Fermi level $E_F = \Lambda$ is sitting on the spectral band $\Delta_n = [T_n, T_{n+1}]$ with the spectral multiplicity $n = n(\Lambda)$, then the specific splitting $\mathcal{L} \longrightarrow \mathcal{L}_\Lambda = L_\Lambda \oplus l_\Lambda$ is applied to the Schrödinger operator on the whole network to create the *Intermediate operator* L_Λ , defined in the orthogonal complement of “open channels” in the wires, see section 2. When matching the outgoing solutions of the corresponding intermediate Schrödinger equation with exponentials in the chopped-off open channels, we obtain scattered waves of the Schrödinger operator on the whole quantum network and calculate the corresponding Scattering matrix. The eigenvalues of the intermediate operators L_Λ below the threshold T_{n+1} generically give rise to resonances of the Schrödinger operator on the whole network, see the formulae (23) and (36) below, or become embedded eigen-

values. In simplest case, when just one quantum well with four equivalent wires attached is involved, see [11], and only one simple *resonance* eigenvalue λ_0^Λ of the Intermediate operator is sitting on the first spectral band Δ_4 , close to the Fermi-level Λ , the Scattering matrix is presented approximately by the corresponding resonance factor (1). This factor contains the pole of the \mathcal{DN} -map at the resonance eigenvalue and the normal derivatives of the corresponding eigenfunction φ_0 projected onto the corresponding four-dimensional entrance subspace $E_+^\Lambda = E_+$ of the *open channels*, - the linear hull of the corresponding cross-section eigenfunctions in the wires:

$$S(\lambda) = -\frac{\mathcal{DN}^\Lambda + iK_+}{\mathcal{DN}^\Lambda - iK_+} \approx \frac{P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s} \rangle}{\lambda - \lambda_0^\Lambda} + iK_+(\lambda_0^\Lambda) - \frac{P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s} \rangle}{\lambda - \lambda_0^\Lambda} - iK_+(\lambda_0^\Lambda). \quad (1)$$

Here K_+ is the exponent obtained from oscillatory solutions in semi-infinite quantum wires and $P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s} \rangle$ is the resonance term associated with the resonance eigenvalue λ_0^Λ and the corresponding eigenfunction φ_0 . It can be presented in standard form $\| P_+ \frac{\partial \varphi_0}{\partial n} \|^2 P_0$ with the orthogonal projection P_0 onto the one-dimensional subspace E_+^0 in E_+ spanned by $P_+ \frac{\partial \varphi_0}{\partial n}$.

The above “one-pole” approximation (1) of the Scattering matrix near the resonance eigenvalue λ_0^Λ is obtained via substitution of the Dirichlet-to-Neumann map of the intermediate operator by the resonance term only, neglecting all non-resonance terms and the contribution from the continuous spectrum. In case of the resonance triadic Quantum Switch, see [11], similar neglecting was possible in a small neighborhood of the resonance eigenvalue. The size of the neighborhood was defined by the “natural” small parameter $\approx 1/20$ which appears from above mentioned comparison of the inverse spacing of eigenvalues of the intermediate operator on the resonance level and the wave-number of the electron in the wire on the resonance energy. We derive also a “few-pole approximation” of the Scattering matrix and interpret it as a Scattering matrix of some solvable model of the network in certain range of energy.

Actual paper has the following plan: after the formal description of the quantum network and introduction of an intermediate operator in the next section 2, we prove in section 3 that the intermediate operator L_Λ is self-adjoint, hence possess a resolvent kernel which has usual properties. Based on these properties we introduce the corresponding Dirichlet-to-Neumann map of the Intermediate operator and connect it with the Dirichlet-to-Neumann map of the Schrödinger operator on the Quantum well. The following section 4 contains the calculation of the Scattering matrix and derivation of the corresponding “one-pole approximation”. Then in section 5 we suggest an interpretation of the “one-pole approximation” of the Scattering matrix on Quantum network as a Scattering matrix of a solvable model presented as a star-shaped graph with a single resonance node. In the last section we discuss briefly some historic details of the perturbation theory on the continuous spectrum.

The aim of our paper is the description of an approach to the transport problem on the network based on the idea of the intermediate operator. This approach is demonstrated in details. But the total volume of this paper is not sufficient to discuss all subtle mathematical

details of each technical step. Hence in couple of places, which are clearly indicated, see for instance discussion of the singular spectrum in Theorem 3.1, we supply just a sketch of the corresponding proof. We plan to return to these questions soon in following publications.

II. INTERMEDIATE OPERATORS

Consider a network on a plane manufactured of several non-overlapping quantum wells (vertex domains) Ω_t , $t = 1, 2, \dots, T$ and a few straight finite or semi-infinite wires ω^m , $l = 1, 2, \dots, M$ of constant width δ_m and length $d_m \leq \infty$ attached to the domains $\Omega_{t_1}, \Omega_{t_2}, \dots$ such that the bottom sections $\gamma_{t_1}^m, \gamma_{t_2}^m$ of the wire ω^m are parts of the piece-wise smooth boundaries $\partial\Omega_{t_1}, \partial\Omega_{t_2}, \dots$ of the domains $\Omega_{t_1}, \Omega_{t_2}, \dots$ respectively. Each wire is attached to one (if the wire is semi-infinite) or two domains (if it is finite), so that the function $m \rightarrow t$ or $m \rightarrow t_1, t_2$ is defined although the inverse function may not be defined, since there may be a few wires ω^m connecting two given domains $\Omega_{t_1}, \Omega_{t_2}$. In our further construction we use slightly extended vertex domains with small “cut-off’s” $\delta\omega^m$ of the wires ω^m attached to them: $\delta\omega^m = \{0 < x < \varepsilon^m\}$, to avoid a discussion of the subtle question of Sobolev smoothness of restrictions of elements from the domain of the operator onto the bottom sections of channels joining the inner angles. Denote by γ_t^m the orthogonal bottom sections of the “shortened” wires with cut-off’s removed (from both ends, if the wire is finite) and attached to the corresponding vertex domains. We will use further former notations Ω_t, ω^m for extended vertex domains and for the shortened wires respectively. The previously described vertex domains and wires will not be used in the following text. We consider the spectral problem for the Schrödinger operator

$$\mathcal{L}u = -\Delta_\mu u + V(x)u = \lambda u \quad (2)$$

on the network $\Omega = \cup_t \Omega_t \cup_m \omega^m$ with zero boundary condition on $\partial\Omega$. The kinetic term $-\Delta_\mu$ containing the tensor μ of effective mass is defined as

$$-\Delta_\mu = \begin{cases} -(2\mu_t)^{-1}\Delta, & \text{if } \in \Omega_t \\ -\frac{1}{2\mu_m^\parallel} \frac{\partial^2}{\partial x^2} - \frac{1}{2\mu_m^\perp} \frac{\partial^2}{\partial y^2} & \text{if } \in \omega^m \end{cases},$$

where μ_t plays the role of the average effective mass in the well Ω_t , x, y are the coordinates along and across the wire ω^m and $\mu_m^\perp, \mu_m^\parallel$ are positive numbers playing the roles of effective masses across and along the wire ω^m respectively. We impose the Meixner condition at the inner corners of the boundary of the domain in form $D(\mathcal{L}) \subset W_2^1(\Omega)$. We assume that the potential V is constant on the wires $V|_{\omega^m} = V_m$ and is a real bounded measurable function V_t on each (extended) vertex domain Ω_t . Without loss of generality we may assume that the overlapping wires do not interact, otherwise we may treat the overlapping as an additional quantum well. The absolutely-continuous spectrum of the operator \mathcal{L} coincides with the absolutely-continuous spectrum of the restriction $\sum_{m=m(t)} \oplus l_m$ of the operator \mathcal{L} onto the sum of all semi-infinite wires ω^m , $m = m(t)$ with zero boundary conditions on the boundary $\cup_m \partial\omega^m$. This fact follows from the Glazman’s splitting technique, [35], see a

discussion in the proof of theorem 3.1 in the next section. The spectrum of the restriction l_m consists of a countable number of branches $\cup_{m=1}^{\infty} \left[V_m + \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2}, \infty \right)$ which correspond to the oscillating modes $e_s^m(y) \exp \pm i \sqrt{2\mu_m^\parallel} \sqrt{\lambda - \left[V_m + \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} \right]} x$, $V_m + \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} < \lambda$ spanned by the eigenfunctions of the cross-section $e_s^m(y) = \sqrt{\frac{2}{\sqrt{2\mu_m^\perp} \delta_m}} \sin \frac{s\pi y}{\sqrt{2\mu_m^\perp} \delta_m}$, $s = 1, 2, \dots$

If the Fermi-level Λ does not coincide with any threshold, $\Lambda \neq V_m + \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2}$, $s = 1, 2, \dots$, then the linear hulls of eigenfunctions of the cross-sections corresponding to the open channels $V_m + \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} < \Lambda$ are considered as entrance subspaces of “open (lower) channels”: $E_+^m(\Lambda) = \bigvee_{s\pi \leq \sqrt{2\mu_m^\perp(\Lambda - V_m)} \delta_m} e_s^m$. The entrance subspaces of “closed (upper) channels” $E_-^m(\Lambda) = \bigvee_{s\pi > \sqrt{2\mu_m^\perp(\Lambda - V_m)} \delta_m} e_s^m = L_2(\gamma^m) \ominus E_+^m(\Lambda)$, correspond to the upper thresholds: $\frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} + V_m > \Lambda$. Denote by $P_\pm^m(\Lambda)$ the orthogonal projections onto the subspaces $E_\pm^m(\Lambda) \subset L_2(\gamma_t^m)$ on the bottom sections of the finite and/or infinite wires ω^m lying on the border of the (extended) vertex domain Ω_t .

An important feature of the above quantum network is the “step-wise” structure of the continuous spectrum of the operator \mathcal{L} with spectral bands of different spectral multiplicities separated by thresholds, see [48]. This property permits us to introduce the corresponding structure of intermediate operators.

Note that elements from the domain of the Schrödinger operator \mathcal{L} on the whole network Ω belong locally (outside a small neighborhood of inner corners) to the proper Sobolev class $D(\mathcal{L}) \subset W_2^2(\Omega_t, loc)$, see [47]. For given Fermi level $\Lambda > 0$ we define an *intermediate operator*, following [9, 10, 11] where the suggested construction was introduced for star-shaped Quantum Switch. The intermediate operator is defined by the same differential expression as the Schrödinger operator \mathcal{L} defined on W_2^2 -smooth functions in the orthogonal sum of spaces of all square-integrable functions on the components $\{\omega^m, \Omega_t\}$ of the network with special boundary conditions at the bottom sections $\gamma_t^m \in \partial\Omega_t$, $t = 1, 2, \dots$ of the wires ω^m :

$$\begin{aligned} P_+^m(\Lambda) u_t \Big|_{\gamma_t^m} &= 0, \quad P_+^m(\Lambda) u^m \Big|_{\gamma_t^m} = 0 \\ P_-^m(\Lambda) \left[u^m \Big|_{\gamma_t^m} - u_t \Big|_{\gamma_t^m} \right] &= 0, \quad P_-^m(\Lambda) \left[\frac{1}{2\mu_m^\parallel} \frac{\partial u^m}{\partial n} \Big|_{\gamma_t^m} - \frac{1}{2\mu_t} \frac{\partial u_t}{\partial n} \Big|_{\gamma_t^m} \right] = 0. \end{aligned} \quad (3)$$

These boundary conditions are meaningful due to Embedding theorems, see [61], because functions from both $W_2^2(\Omega_t, loc)$, $W_2^2(\omega^m)$ have boundary values in proper sense on the elements of the common boundary $\partial\omega^m \cap \partial\Omega_t$ - on the bottom sections γ_t^m of the (shortened) wires. We also assume that the Meixner conditions are fulfilled at the inner corners for the component u_t of the element in the vertex domains. The obtained split operator is denoted further in this section by $\hat{\mathcal{L}}_\Lambda$, and the whole domain of it in $\cup_t W_2^2(\Omega_t, loc) \oplus \cup_m W_2^2(\omega^m)$ is denoted by $D(\hat{\mathcal{L}}_\Lambda)$. The Meixner condition can be presented as $D(\hat{\mathcal{L}}_\Lambda) \subset W_2^1(\Omega)$.

To present the above boundary conditions in a more compact form we can introduce orthogonal sums of upper (closed) and lower (open) entrance spaces $\sum_m \oplus (E_t^m)_\pm := E_{t,\pm}$ on

the wires attached to the domain Ω_t . We introduce also similar notations for the corresponding projections $P_{t,\pm}\mathbf{u}^\omega$ of the vectors $\sum_m u^m := \mathbf{u}_t^\omega$ obtained via restriction of functions defined on the wires attached to the given domain Ω_t onto the bottom sections $\gamma_t^m \in \partial\Omega_t \cap \partial\omega^m$. Similarly we can introduce the restrictions of the functions u_t defined in Ω_t onto the sum $\Gamma_t = \cup_m \gamma_t^m$ of all bottom sections γ_t^m of the wires ω^m attached to the domain Ω_t :

$$\mathbf{u}_{\Omega_t} = u_t \Big|_{\Gamma_t}$$

and the corresponding projections $\sum_m P_{t,\pm}^m = P_{t,\pm}$, and then form an orthogonal sum:

$$\mathbf{u}_\Omega = \sum_t \oplus u_{\Omega_t}, \quad P_\pm \mathbf{u}_\Omega = \sum_{t,m} \oplus P_{t,\pm}^m \mathbf{u}_{\Omega_t}.$$

Now the above boundary conditions can be re-written in a compact form as

$$P_+ \mathbf{u}_\Omega = P_+ \mathbf{u}^\omega = 0, \quad P_- [\mathbf{u}_\Omega - \mathbf{u}^\omega] = 0, \quad P_- \left[\frac{1}{2\mu_\Omega} \frac{\partial \mathbf{u}_\Omega}{\partial n} - \frac{1}{2\mu^\parallel} \frac{\partial \mathbf{u}^\omega}{\partial n} \right] = 0. \quad (4)$$

Here $\mu_\Omega, \mu^\parallel$ are diagonal tensors composed of values of the average effective masses in domains Ω_t and along the wires ω^m respectively. The boundary condition 4 may be interpreted as a ‘‘chopping-off’’ condition in all open (lower) channels $\frac{s^2 \pi^2}{2\mu_\omega^\perp \delta_m^2} + V_m < \Lambda$ and a ‘‘partial matching condition’’ in all closed (upper) channels $\frac{s^2 \pi^2}{2\mu_\omega^\perp \delta_m^2} + V_m > \Lambda$. The restrictions $\hat{l}^m(\Lambda)$ of the split operator $\hat{\mathcal{L}}$ onto the invariant subspaces $\mathcal{H}_+^m = \bigvee_{\frac{s^2 \pi^2}{2\mu_\omega^\perp \delta_m^2} + V_m < \Lambda} e_s^m \times L_2(0, d_m) = E_+^m \times L_2(0, d_m)$ which correspond to the (open) channels $\frac{s^2 \pi^2}{2\mu_\omega^\perp \delta_m^2} + V_m < \Lambda$, are self-adjoint operators and admit spectral analysis in explicit form. We denote by \hat{l}_Λ the orthogonal sum of all operators $\hat{l}_s^m(\Lambda)$ in all open channels. The restriction \hat{L}_Λ of $\hat{\mathcal{L}}$ onto the complementary invariant subspace is also a self-adjoint operator :

$$\hat{L}_\Lambda = \hat{\mathcal{L}} \ominus \left\{ \sum_{\frac{s^2 \pi^2}{2\mu_\omega^\perp \delta_m^2} + V_m < \Lambda} \oplus \hat{l}_s^m(\Lambda) \right\} := \hat{\mathcal{L}} \ominus \hat{l}_\Lambda.$$

The above chopping-off construction can be applied either to open channels in all wires, both finite and infinite, resulting in the above operators \hat{L}_Λ and \hat{l}_Λ , or applied to the semi-infinite open channels only, resulting in corresponding operators L_Λ, l_Λ respectively, $\mathcal{L}_\Lambda = L_\Lambda \oplus l_\Lambda$. One of the intermediate operators : \hat{L}_Λ or L_Λ can be more convenient for calculating the Scattering matrix, depending on the architecture of the network. In the remaining part of this paper we choose L_Λ as an intermediate operator, chopping off only the open channels in semi-infinite wires.

Some useful modification of the above chopping-off construction is also convenient: for given value Λ of the Fermi level one can choose the number $\Lambda_1 > \Lambda$ and split the operator \mathcal{L} as $L_{\Lambda_1} \oplus l_{\Lambda_1}$ with l_{Λ_1} , containing several closed channels, for given Fermi level, in the finite lower group. The formulae which are derived for the Scattering matrix in this case look slightly less elegant because of excessive number of matching conditions. But an essential

gain of this modification of the intermediate operator is the shift of the lower border of the continuous spectrum of the intermediate operator beyond the level Λ_1 , at the minor price of appearance of a finite number of eigenvalues the intermediate operator L_{Λ_1} below Λ_1 . This modification of the construction of the intermediate operator will be used in course of the proof of the Theorem 3.1 and further in section 5, see also a relevant “physical” motivation in the beginning of section 5. We postpone the standard derivation of the corresponding formulae for the Scattering matrix to the following publication, but concentrate further mainly on the contribution to the Scattering matrix from the discrete spectrum of L_Λ .

III. DIRICHLET-TO-NEUMANN MAP

When studying Scattering on one-dimensional Quantum Networks one obtains the Scattered waves of the operator \mathcal{L} on the network via matching solutions of the split Schrödinger operator \mathcal{L}_Λ with elementary exponentials, or, generally, Jost functions, in the semi-infinite wires at infinity, see for instance [17, 33, 40, 89]. In case of more realistic two-dimensional wires matching of solutions from neighboring domains on common boundary is also an initial step of the perturbation procedure.

Now we focus on the multi-dimensional techniques of matching based on a special version of the Dirichlet-to-Neumann map [68, 90] modified for the intermediate operator on the Quantum Network. We need, first of all, the self-adjointness of the intermediate operator, the corresponding Green function and the Poisson map. Then, based on them, we suggest an algorithm for the construction of the Dirichlet-to-Neumann map of the intermediate operator which gives eventually the corresponding Scattering matrix.

Most of facts collected in the following statement are very well known, but scattered in literature, beginning from [84]. Lot's of important analytic facts we need, and even in stronger form, can be found in [47, 48].

Theorem III.1 *Consider the operators $\mathcal{L}_\Lambda, L_\Lambda, l_\Lambda, \mathcal{L}_\Lambda = L_\Lambda \oplus l_\Lambda$, defined by the differential expression (2), the above boundary conditions (4), or just matching conditions on Γ , and Meixner condition at the inner corners of the boundary of the whole network. The domains of the operators consist of all properly smooth functions defined on the sum of all open semi-infinite channels $\mathcal{H}_+(\Lambda) = \sum_m \mathcal{H}_+^m(\Lambda)$ and in the orthogonal complement $\mathcal{H}_-(\Lambda) = L_2(\Omega) \ominus \sum_m \mathcal{H}_+^m(\Lambda)$ respectively. The absolutely-continuous spectra $\sigma(l_\Lambda), \sigma(\mathcal{L}_\Lambda)$ of the operators $l_\Lambda, \mathcal{L}_\Lambda$ coincide with the joining of all lower and upper branches in semi-infinite wires, respectively:*

$$\begin{aligned}\sigma(l_\Lambda) &= \cup_{\left\{ \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} < \Lambda - V_m \right\}} \left[\frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} + V_m, \infty \right), \\ \sigma(L_\Lambda) &= \cup_{\left\{ \frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} > \Lambda - V_m \right\}} \left[\frac{s^2 \pi^2}{2\mu_m^\perp \delta_m^2} + V_m, \infty \right).\end{aligned}$$

The absolutely-continuous spectrum $\sigma(\mathcal{L})$ of the operator \mathcal{L} coincides with the absolutely-continuous spectrum of the orthogonal sum $\mathcal{L}_\Lambda = L_\Lambda \oplus l_\Lambda$:

$$\sigma(\mathcal{L}) = \sigma(\mathcal{L}_\Lambda) = \sigma(l_\Lambda) + \sigma(L_\Lambda)$$

Besides the absolutely continuous spectrum, the operators \mathcal{L} and L_Λ may have a finite number of eigenvalues below the threshold of the absolutely-continuous spectrum and a countable sequence of embedded eigenvalues accumulating at infinity. The singular continuous spectrum of both \mathcal{L} , \mathcal{L}_Λ is absent.

The original operator \mathcal{L} on the whole network is obtained from the split operator $\mathcal{L}_\Lambda = L_\Lambda \oplus l_\Lambda$ via the finite-dimensional perturbation replacing the first of the boundary conditions (4) by the corresponding partial matching boundary condition in the lower channels.

Proof To verify the self-adjointness of the operator \mathcal{L}_Λ it is sufficient to prove that the operator \mathcal{L}_Λ is symmetric on the domain consisting of all properly smooth functions satisfying the above boundary conditions and it's adjoint is symmetric too. Then the operator L_Λ is self-adjoint as a difference of self-adjoint operators $\mathcal{L} \ominus l_\Lambda$.

We introduce the notation $\cup_{m,s}\gamma_s^m := \Gamma$ and consider the decomposition of the network $\Omega = (\cup_m \omega^m) \cup (\cup_s \Omega_s)$. Then integrating by parts with functions continuously differentiable on each component of the above decomposition we may present the boundary form of the Schrödinger operator L without boundary conditions in terms of jumps $[\mathbf{u}] = u^\omega - u^\Omega$, $\left[\frac{\partial \mathbf{u}}{\partial n}\right] = \frac{1}{2\mu_m^\parallel} \frac{\partial u^\omega}{\partial n} - \frac{1}{2\mu_t} \frac{\partial u_\Omega}{\partial n}$ of the functions, and ones of the normal derivatives on bottom sections of the wires and the corresponding mean values $\{\mathbf{u}\} = \frac{1}{2} \{u^\omega + u_\Omega\}$, $\left\{\frac{\partial \mathbf{u}}{\partial n}\right\} = \frac{1}{2} \left\{\frac{1}{2\mu_m^\parallel} \frac{\partial u^\omega}{\partial n} + \frac{1}{2\mu_t} \frac{\partial u_\Omega}{\partial n}\right\}$:

$$\begin{aligned} \langle \mathcal{L}\mathbf{u}, \mathbf{v} \rangle - \langle \mathbf{u}, \mathcal{L}\mathbf{v} \rangle = \\ \int_\Gamma \left(\left[\frac{\partial \mathbf{u}}{\partial n}\right] \{\bar{\mathbf{v}}\} - \{\mathbf{u}\} \left[\frac{\partial \bar{\mathbf{v}}}{\partial n}\right] \right) d\Gamma + \\ \int_\Gamma \left(\left\{\frac{\partial \mathbf{u}}{\partial n}\right\} [\bar{\mathbf{v}}] - [\mathbf{u}] \left\{\frac{\partial \bar{\mathbf{v}}}{\partial n}\right\} \right) d\Gamma. \end{aligned}$$

Denote by P_+^Λ the orthogonal sum of orthogonal projections onto the sum E_+^Λ of the entrance subspaces of the lower (open) channels in $L_2(\Gamma)$ and by P_-^Λ the complementary projection, $I = P_+^\Lambda + P_-^\Lambda$. Inserting this decomposition of unity into the integration over $\Gamma = \cup_{m,t}\gamma_t^m$ we can see that the above boundary form is equal to

$$\begin{aligned} \int_\Gamma \left(P_+^\Lambda \left[\frac{\partial \mathbf{u}}{\partial n}\right] P_+^\Lambda \{\bar{\mathbf{v}}\} - P_+^\Lambda \{\mathbf{u}\} P_+^\Lambda \left[\frac{\partial \bar{\mathbf{v}}}{\partial n}\right] \right) d\Gamma + \\ \int_\Gamma \left(P_-^\Lambda \left[\frac{\partial \mathbf{u}}{\partial n}\right] P_-^\Lambda \{\bar{\mathbf{v}}\} - P_-^\Lambda \{\mathbf{u}\} P_-^\Lambda \left[\frac{\partial \bar{\mathbf{v}}}{\partial n}\right] \right) d\Gamma + \\ \int_\Gamma \left(P_+^\Lambda \left\{\frac{\partial \mathbf{u}}{\partial n}\right\} P_+^\Lambda [\bar{\mathbf{v}}] - P_+^\Lambda [\mathbf{u}] P_+^\Lambda \left\{\frac{\partial \bar{\mathbf{v}}}{\partial n}\right\} \right) d\Gamma + \\ \int_\Gamma \left(P_-^\Lambda \left\{\frac{\partial \mathbf{u}}{\partial n}\right\} P_-^\Lambda [\bar{\mathbf{v}}] - P_-^\Lambda [\mathbf{u}] P_-^\Lambda \left\{\frac{\partial \bar{\mathbf{v}}}{\partial n}\right\} \right) d\Gamma. \end{aligned}$$

One can see from (3) that the operator L supplied with the above boundary conditions is symmetric. Vice versa, if L^+ is the adjoint operator then the boundary form with $\mathbf{u} \in$

$D(L)$, $\mathbf{v} \in D(L^+)$ vanishes. Then $P_+^\Lambda \{\mathbf{v}\} = 0$, $P_+^\Lambda [\mathbf{u}] = 0$ follows from arbitrariness of values of the normal derivatives of the function $P_+^\Lambda \mathbf{v}$ on both sides of γ_t^m . Similarly another two boundary conditions (3) for elements $\mathbf{v} \in D(L^+)$ may be verified based on the arbitrariness of values of $P_-^\Lambda \{\mathbf{u}\}$ and $P_-^\Lambda \left\{ \frac{\partial \mathbf{u}}{\partial n} \right\}$. Hence the adjoint operator is symmetric and thus self-adjoint.

The restriction l_Λ of the operator \mathcal{L}_Λ onto the lower channels is obviously a self-adjoint operator. We call it the *trivial component* of \mathcal{L}_Λ . Hence the restriction L_Λ of it onto the orthogonal complement of lower channels- the *nontrivial component* of \mathcal{L}_Λ - is a self-adjoint operator too. The absolutely continuous spectrum $\sigma(L_\Lambda)$ coincides with the absolutely-continuous spectrum of the restriction of the original operator \mathcal{L} on the upper channels $\sigma(L_\Lambda) = \left[\lambda_{min}^\Lambda, \infty \right)$,

$$\lambda_{min}^\Lambda = \min_{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m > \Lambda} \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m.$$

Here is a sketch of the proof of this elementary statement. Consider a splitting of \mathcal{L} with higher “formal Fermi level” $\Lambda_1 \gg \Lambda$. The absolutely - continuous spectrum of the operator \mathcal{L} is the same as an absolutely-continuous spectrum of the split operator, due to the finite-dimensionality of the perturbation: it is a sum $\sigma(l_{\Lambda_1})$ of absolutely continuous lower branches corresponding to the trivial component and the absolutely continuous spectrum of L_{Λ_1} . Hence it suffice to prove, that the spectrum of L_{Λ_1} below the threshold λ_{min}^Λ is discrete.

Consider inside the wires a solution of the homogeneous equation $L_{\Lambda_1} u = \lambda u$ with $\lambda < \Lambda < \Lambda_1$. This equation admits separation of variables inside the wires

$$-\frac{1}{2\mu^\parallel} \frac{\partial^2 u}{\partial x^2} - \frac{1}{2\mu^\perp} \frac{\partial^2 u}{\partial y^2} + V_m u = \lambda u,$$

$$u = \sum_{\frac{1}{2\mu^\perp} \frac{\pi^2 l^2}{\delta^2} + V_m \geq \Lambda_1} c_l \sin \frac{\pi l}{\delta \sqrt{2\mu^\perp}} e^{-\sqrt{2\mu^\parallel} \sqrt{\frac{\pi^2 l^2}{\delta^2 2\mu^\perp} + V_m - \lambda} x}.$$

Then each locally smooth solution of this equation is exponentially decreasing in the wires $|u|(x, y) \leq C_u e^{-\sqrt{2\mu^\parallel} |\Lambda_1 - \Lambda|^{1/2} x}$. In particular, the Green-function of the operator L_Λ is square-integrable, hence defines a bounded operator, if exists for given $\lambda < \Lambda_1$. Hence the spectrum of the operator L_{Λ_1} does not have a purely continuous component on the interval $(-\infty, \Lambda_1)$. Assume that there exist an infinite sequence of eigenvalues $\{\lambda_r\}$ which is convergent to $\Lambda_2 \leq \Lambda$. Without loss of generality one may assume that $\lambda_r \leq \frac{\Lambda + \Lambda_1}{2}$ for each r . The (normalized) eigenfunctions are continuous due to embedding theorems,

$$\sup |\varphi_r| \leq C \Lambda,$$

with some dimensional constant C , hence they are exponentially decreasing in the wires:

$$|\varphi_r|(x, y) \leq C \Lambda e^{-\sqrt{2\mu^\parallel} \sqrt{\frac{\Lambda_1 - \Lambda}{2}} x},$$

due to maximum principle, and admit an uniform estimate of “the tail” in the wires $\int_M^\infty |\varphi_r|^2(x, y) dm \leq C^2 \frac{\Lambda^2}{\sqrt{\mu^\parallel} (\Lambda_1 - \Lambda)}$. Then any linear combination $\varphi = \sum_r c_r \varphi_r$ of the eigenfunctions at least admits the estimate

$$|\varphi|_{Lip^{2/5}}^2 < C^2 |L\varphi|_{L_2}^2 = C^2 \sum_r c_r^2 |L\varphi_r|_{L_2}^2 \leq C^2 \left(\frac{\Lambda_1 + \Lambda}{2} \right)^2 |\varphi|_{L_2}^2$$

due to the Parseval identity, and the estimation of the tail

$$\int_M^\infty |\varphi|^2(x, y) dx dy \leq C^2 \frac{\Lambda^2}{\sqrt{\mu^\parallel} (\Lambda_1 - \Lambda)}.$$

Now compactness of the unit ball in the subspace of all linear combinations of eigenfunctions φ_r follows from embedding theorems on the compact part $\Omega_M = \Omega \cup \{x^2 + y^2 \leq M\}$ of the network and the uniform estimation of the tails. The compactness implies the finiteness of the number of the eigenvalues of L_{Λ_1} below Λ .

The absolutely-continuous spectrum of the operator l_Λ has constant multiplicity $\dim E_+^\Lambda$ on semi-infinite interval $(\lambda_{max}^\Lambda, \infty)$, where

$$\lambda_{max}^\Lambda = \max_{\frac{\pi^2 l_m^2}{2\mu_m^\perp \delta_m^2} + V_m < \Lambda} \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m.$$

On the spectral band $\Delta_\Lambda = (\lambda_{max}^\Lambda, \lambda_{min}^\Lambda)$ the spectral multiplicity of the absolutely continuous spectra of both operators \mathcal{L}_Λ , \mathcal{L} is equal to $\dim E_+^\Lambda$. In our case embedded eigenvalues are possible, but only a finite number of them on any finite sub-interval of the continuous spectrum, see for instance [23, 73].

Singular spectrum of the Schrödinger operator with compactly supported potential on a finite joining of standard domains, is, generically, absent, see the discussion in [82], but the proof of this fact in special cases needs an accurate investigation. In our special case absence of the singular continuous spectrum may be derived from the fact that the partial boundary conditions imposed on the bottom sections of semi-infinite wires define the finite-dimensional perturbation of the operator \mathcal{L} . Recently absence of singular spectrum in wave-guiding systems was discussed in [50, 51] by the method which may be applied in our situation too. Nevertheless we supply below a sketch of possible proof based on classical ideas.

Basic definition of H -smoothness in [82], volume 4, XXXIII.7 admits a local formulation for the operator A , $R_\lambda \mathcal{H} \subset D(A)$ in Hilbert space \mathcal{H} with respect to the operator H , $R_\lambda = (H - \lambda I)$, see [97]. Conditions of local smoothness are actually derived in the theorem XXXIII.25 of [82]. They imply the corresponding local conditions of absence of the singular spectrum of $H + A$ on the interval (a, b) , if we know that operator H does not have singular spectrum on the interval and succeed to verify the local smoothness of the perturbation A . The deficiency elements used in course of the construction of the split operator for real λ below the threshold λ_{min}^Λ of the absolutely continuous spectrum of \mathcal{L} satisfy the Helmholtz equation in the wires and hence decrease exponentially at infinity as $\exp\left(-[\lambda_{min}^\Lambda - \lambda]^{1/2} x\right)$.

Hence the finite-dimensional perturbation of $\mathcal{L}_\Lambda = L_\Lambda \oplus l_\Lambda \rightarrow \mathcal{L}$ is relatively smooth below the threshold λ_{min}^Λ , which implies absence of the singular spectrum of H .

The last statement of the theorem is obvious, see the corresponding calculations below in course of derivation the formula (24) for the Scattering matrix in terms of the DN-map of the intermediate operator. This accomplishes the proof of the theorem.

Note that accumulation of embedded eigenvalues of the operator \mathcal{L} to a finite point is discussed in [24], where also an example of the Schrödinger operator with exponentially decreasing electric field and accumulation of eigenvalues to the threshold is suggested. Note that presence of slowly-decreasing potentials in the wires implies, generally, an accumulation of the embedded eigenvalues to thresholds. This general fact was discovered recently in [44]. In our case accumulation of eigenvalues on any finite interval of the spectral parameter is impossible because potentials on the semi-infinite wires are constant (the electric field is compactly supported).

Assume that the eigenfunctions of the absolutely-continuous spectrum of the operator L_Λ and its Green function $G_\Lambda(x, s)$ are already constructed:

$$-\Delta_\mu G + VG = \lambda G + \delta(x - s).$$

Then we can construct the Dirichlet-to-Neumann map (DN-map) of the operator L_Λ . The standard DN-map is described in [68, 90]. The modified DN-map of the operator L_Λ can be obtained via *projection* onto the lower channels of the boundary current $\frac{1}{2\mu_\Omega} P_+^\Lambda \frac{\partial u}{\partial n} \Big|_\Gamma$ of the solution of the homogeneous equation $lu - \lambda u = 0$ with the boundary condition $u \Big|_\Gamma = u_\Gamma \in E_+^\Lambda$, for regular values of the spectral variable λ . The solution u tends to zero at infinity if $\Im \lambda \neq 0$. It may be constructed using the resolvent kernel $G_\Lambda(x, x', \lambda)$ of the operator L_Λ . The corresponding Poisson map is given by the formula:

$$\mathcal{P}^\Lambda u_\Gamma(x) = - \int_\Gamma \frac{1}{2\mu_\Omega} \frac{\partial G_\Lambda(x, s, \lambda)}{\partial n_s} u_\Gamma(s) ds.$$

Then the corresponding DN-map of the operator L_Λ is

$$\frac{1}{2\mu_\Omega} \frac{\partial \mathcal{P}^\Lambda u_\Gamma}{\partial n} = - \int_\Gamma \frac{1}{(2\mu_\Omega)^2} \frac{\partial^2 G_\Lambda(x, s, \lambda)}{\partial n_x \partial n} u_\Gamma(s) ds := \mathcal{DN}^\Lambda u_\Gamma.$$

The normal current $\frac{\partial \mathcal{P}^\Lambda u_\Gamma}{\partial n}$ belongs to $W_2^{1/2-\varepsilon}$, $\varepsilon > 0$, hence the formal integral operator $\int_\Gamma \frac{\partial^2 G_\Lambda(x, s, \lambda)}{\partial n_x \partial n} u_\Gamma(s) ds$ is unbounded in $W_2^{3/2-\varepsilon}(\Gamma)$. However, since $E_+^\Lambda \subset W_2^{3/2-\varepsilon}(\Gamma)$ the projection of the normal current onto E_+^Λ is bounded from $W_2^{3/2-\varepsilon}(\Gamma)$ to $W_2^{3/2-\varepsilon}(\Gamma)$, hence

$$\mathcal{DN}^\Lambda u_\Gamma = -P_+^\Lambda \int_\Gamma \frac{\partial^2 G_\Lambda(x, s, \lambda)}{\partial n_x \partial n} u_\Gamma(s) ds \in W_2^{3/2-\varepsilon}(\Gamma),$$

$$\mathcal{DN}^\Lambda : W_2^{3/2-\varepsilon}(\Gamma) \longrightarrow W_2^{3/2-\varepsilon}(\Gamma).$$

According to the previous theorem 3.1 there are only a finite number of eigenvalues λ_r^Λ of the operator L_Λ in any compact domain of the complex plane $\{\lambda\}$. Then the following spectral

representation is valid for the corresponding DN-map:

$$\begin{aligned} \mathcal{DN}^\Lambda(\lambda) = & \sum_r \frac{1}{(2\mu_\Omega)^2} \frac{P_+^\Lambda \frac{\partial \varphi_r(x)}{\partial n_x} \rangle \langle P_+^\Lambda \frac{\partial \varphi_r(s)}{\partial n_r}}{\lambda - \lambda_r^\Lambda} + \\ & \sum_{V_m + \frac{\pi^2 l^2}{2\mu_m \delta_m^2} > \Lambda} \int_{\frac{\pi^2 l^2}{\delta_m^2}}^\infty \frac{1}{(2\mu_\Omega)^2} \frac{P_+^\Lambda \frac{\partial \varphi_{\rho,l}(x)}{\partial n_x} \rangle \langle P_+^\Lambda \frac{\partial \varphi_{\rho,l}(s)}{\partial n_s}}{\lambda - \rho} d\rho, \end{aligned} \quad (5)$$

where the normal derivatives are calculated on Γ and the integration is extended over all branches of the absolutely-continuous spectrum of the operator L_Λ emerging from the upper thresholds $\frac{\pi^2 l^2}{2\mu_m \delta_m^2} + V_m > \Lambda$. The tensor μ_Ω of the effective mass is diagonal, as defined in the previous section. Based on above analysis one can prove that $P_+^\Lambda \frac{\partial \varphi}{\partial n} \Big|_\Gamma \in W_2^{3/2-\varepsilon}$ and the integral and the series (5) are convergent in proper sense due to the presence of the finite-dimensional projection P_+^Λ onto the entrance subspace $E_+^\Lambda \subset W_2^{3/2-\varepsilon}$, see a similar reasoning in [69]. The whole finite-dimensional matrix-function $\mathcal{DN}^\Lambda(\lambda)$ is bounded in $W_2^{3/2-\varepsilon}$ with poles of first order at the eigenvalues λ_s^r of the operator L_Λ and cuts along the upper branches $\left[\frac{\pi^2 l^2}{2\mu_m \delta_m^2} + V_m, \infty \right)$ of the absolutely-continuous spectrum.

Practical calculation of the DN-map $\mathcal{DN}^\Lambda(\lambda)$ by the above formula (5) requires knowing of eigenvalues and eigenfunctions of discrete and absolutely-continuous spectrum of the intermediate operator L_Λ .

Another expression for the DN-map may be also useful. This expression for \mathcal{DN}^Λ is obtained in terms of matrix elements of the DN-map \mathcal{DN} of the compact part Ω_0 of the network with all semi-infinite wires having zero boundary condition on their bottom sections.

The spectrum of the Schrödinger operator L_0 on the “extended” compact part Ω_0 of the network with zero boundary conditions on the bottom sections of the semi-infinite channels is discrete. The DN-map of L_0 is an operator with the generalized kernel

$$\mathcal{DN}(x, s, \lambda) = -\frac{1}{(2\mu_\Omega)^2} \frac{\partial^2 G_0(x, s, \lambda)}{\partial n_x \partial n_s}$$

$$\mathcal{DN}(\lambda) : W_2^{3/2-\varepsilon}(\partial\Omega_0) \longrightarrow W_2^{1/2-\varepsilon}(\partial\Omega_0).$$

We consider the restricted \mathcal{DN} -map framed by projections on $E = L_2(\Gamma)$:

$$P_E \mathcal{DN}(\lambda) P_E.$$

Denoting by $\phi_r(x)$ the orthogonal projections onto E of the boundary currents $\frac{\partial \varphi_r(x)}{\partial n_x}$ of eigenfunctions of the operator L_0 we obtain the spectral representation of the framed DN-map of the operator L_0 by the formal series

$$P_E \mathcal{DN}(\lambda) P_E = \sum_r \frac{1}{(2\mu_\Omega)^2} \frac{P_E \frac{\partial \varphi_r(x)}{\partial n_x} \rangle \langle P_E \frac{\partial \varphi_r(s)}{\partial n_r}}{\lambda - \lambda_r^0} := \sum_r \frac{1}{(2\mu_\Omega)^2} \frac{\phi_r(x) \rangle \langle \phi_r(s)}{\lambda - \lambda_r^0},$$

which is convergent in weak sense on smooth elements from E_+ .

To derive the formula connecting the DN-maps of the operator L_0 and one of the intermediate operator we present the framed DN-map of L_0 as a matrix with respect to the orthogonal decomposition $L_2(\Gamma) = E_+^\Lambda \oplus E_-^\Lambda$ into entrance subspaces of the open and closed channels. Based on the observation $E_+ \in W_2^{3/2-\varepsilon}$, we see that the matrix elements $\mathcal{DN}_{+-}^\Lambda(\lambda)$ are operators mapping $E_\pm \dots$ into $E_\pm \dots$ respectively (for regular λ)

$$P_E \mathcal{DN} P_E = \begin{pmatrix} P_+^\Lambda (\mathcal{DN}) P_+^\Lambda & P_+^\Lambda (\mathcal{DN}) P_-^\Lambda \\ P_-^\Lambda (\mathcal{DN}) P_+^\Lambda & P_-^\Lambda (\mathcal{DN}) P_-^\Lambda \end{pmatrix} := \begin{pmatrix} \mathcal{DN}_{++} & \mathcal{DN}_{+-} \\ \mathcal{DN}_{-+} & \mathcal{DN}_{--} \end{pmatrix}. \quad (6)$$

Consider the basis $\{e_l^m\}$ of all entrance vectors of closed channels, $\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m > \Lambda$, and introduce the diagonal matrix K_-^Λ with elements $k_l^m = -\sqrt{2\mu_m^\parallel} \sqrt{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m - \Lambda}$, on the entrance subspaces $E_{i,-}^m$ of closed channels $\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m > \Lambda$. The corresponding operator $K_-^\Lambda(\lambda) := K_-(\lambda)$ has a bounded inverse $(K_-)^{-1} : W_2^{1/2-\varepsilon} \rightarrow W_2^{3/2-\varepsilon}$, $\varepsilon \geq 0$ for λ below the minimal upper threshold λ_{min}^Λ .

Let $\mathbf{u} = \{u_t, u^m\}$ be a solution of the Schrödinger equation on the network with the boundary data $u_\Gamma \in E_+$ on the sum Γ of bottom sections of the semi-infinite open channels and matching boundary conditions in the upper channels

$$P_+^\Lambda \mathbf{u}_\Omega = u_\Gamma, \quad P_-^\Lambda [\mathbf{u}_\Omega - \mathbf{u}_\omega] = 0, \quad P_-^\Lambda \left[\frac{1}{2\mu_\Omega} \frac{\partial \mathbf{u}_\Omega}{\partial n} - \frac{1}{2\mu_\omega^\parallel} \frac{\partial \mathbf{u}^\omega}{\partial n} \right] = 0$$

and standard matching boundary conditions on all bottom sections of the finite wires. Denote by u_- the projection of the solution onto the entrance subspace E_- in the upper channels in the semi-infinite wires.

We calculated above the DN-map of the operator L_Λ as a projection onto E_+ of the boundary current

$$\mathcal{DN}^\Lambda u_\Gamma = \frac{1}{2\mu_\Omega} P_+ \frac{\partial \mathbf{u}}{\partial n}$$

of the outgoing [59] solution u of the homogeneous equation $\mathcal{L}_\Lambda u = \lambda u$ with the boundary condition $u|_\Gamma = u_\Gamma \in E_+$ and the matching conditions in upper channels:

$$P_- [\mathbf{u}_\Omega - \mathbf{u}_\omega] = 0, \quad P_- \left[\frac{1}{2\mu_\Omega} \frac{\partial \mathbf{u}_\Omega}{\partial n} - \frac{1}{2\mu_\omega^\parallel} \frac{\partial \mathbf{u}^\omega}{\partial n} \right] = 0.$$

Due to (6) this gives the following system of equations:

$$\begin{aligned} P_+ (\mathcal{DN}) P_+ u_\Gamma + P_+ (\mathcal{DN}) P_+ u_- &= \mathcal{DN}^\Lambda u_\Gamma, \\ P_- (\mathcal{DN}) P_+ u_\Gamma + P_- (\mathcal{DN}) P_- u_- &= K_- u_-. \end{aligned}$$

Eliminating u_- we obtain the following statement:

Theorem III.2 *The DN-map \mathcal{DN}^Λ of the intermediate operator L_Λ is connected with the DN-map (\mathcal{DN}) of the operator L_0 on the compact part Ω_0 of the network Ω by the formula*

$$\mathcal{DN}^\Lambda = P_+^\Lambda (\mathcal{DN}) P_+^\Lambda - P_+^\Lambda (\mathcal{DN}) P_-^\Lambda \frac{I}{P_-^\Lambda (\mathcal{DN}) P_-^\Lambda - K_-} P_-^\Lambda (\mathcal{DN}) P_+^\Lambda. \quad (7)$$

The obtained formula for \mathcal{DN}^Λ can be convenient when considering an independent shrinking [56] of vertex domains and the quantum wires of the network, if the local geometry of the network permits it. The DN-map of the Schrödinger operator on the system of channels is contained in (7) in explicit form, i.e. as diagonal matrices of square roots: the negative on the real axis matrix $K_- = \text{diag} \left\{ -\sqrt{2\mu_m^\parallel} \sqrt{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m - \lambda} \right\}$ and purely imaginary matrix with a positive imaginary part (on real axis) $iK_+ = i \text{diag} \left\{ \sqrt{2\mu_m^\parallel} \sqrt{\lambda - \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} - V_m} \right\}$. Matrix elements of the DN-map of the Schrödinger operator L_0 in the domain Ω_0 are rational functions of the spectral parameter with singularities at the eigenvalues of the operator L_0 .

Remark Note that the denominator $(\mathcal{DN})_- - K_- := \mathbf{D}(\lambda)$ in the above formula (7) can be conveniently transformed due to the invertibility of $K_- = -|K_-|$ on the Fermi-level:

$$\mathbf{D}(\lambda) = P_-^\Lambda (\mathcal{DN}) P_-^\Lambda - K_- = |K_-|^{1/2} \left[I + |K_-|^{-1/2} (\mathcal{DN})_- |K_-|^{-1/2} \right] |K_-|^{1/2},$$

where the operator in the bracket is acting in $W_2^{3/4-\varepsilon}$ and may be extended onto L_2 by continuity.

Our nearest aim is investigation of its structure and establishing conditions of invertibility of the denominator $\mathbf{D}(\lambda)$.

We can present the operator \mathcal{DN} via Hilbert identity, see [68], with the corresponding Poisson kernels P_H for large positive H :

$$\mathcal{DN}(\lambda) = \mathcal{DN}(-H) - (\lambda + H)\mathcal{P}_H^+ \mathcal{P}_H - (\lambda + H)^2 \mathcal{P}_H^+ (L_0 - \lambda I)^{-1} \mathcal{P}_H. \quad (8)$$

The first summand acts as an operator from $W_2^{3/2-\varepsilon}$ to $W_2^{1/2-\varepsilon}$. Hence, substituting (8) into the preceding formula for the denominator we notice, due to $E_+ \subset W_2^{3/2-\varepsilon}$, and invertibility of $K_- : W_2^{1/2-\varepsilon} \rightarrow W_2^{3/2-\varepsilon}$, that the operator $|K_-|^{-1/2} (\mathcal{DN})_- |K_-|^{-1/2}$ is presented as

$$\begin{aligned} & |K_-|^{-1/2} P_-^\Lambda \mathcal{DN}(-H) P_-^\Lambda |K_-|^{-1/2} - \\ & - (\lambda + H) |K_-|^{-1/2} P_-^\Lambda \mathcal{P}_H^+ \mathcal{P}_H P_-^\Lambda |K_-|^{-1/2} - \\ & (\lambda + H)^2 |K_-|^{-1/2} P_-^\Lambda \mathcal{P}_H^+ (L_0 - \lambda I)^{-1} \mathcal{P}_H P_-^\Lambda |K_-|^{-1/2}. \end{aligned} \quad (9)$$

The first term in this expression is a bounded operator in $W_2^{3/2-0}$, and may be extended as a bounded operator onto $E = L_2(\Gamma)$. Others terms are compact in E . Moreover, one can prove, following similar reasoning in [69], that the operator $|K_-|^{-1/2} P_-^\Lambda \mathcal{P}_H^+ (L_0 - \lambda I)^{-1} \mathcal{P}_H P_-^\Lambda |K_-|^{-1/2}$ is trace-class operator in $E = L_2(\Gamma)$.

We will use the decomposition of the last term into the series of polar summands, and separate the resonance term $\frac{\phi_0 \rangle \langle \phi_0}{\lambda - \lambda_0}$, with $\phi_0 = P_- \frac{\partial \varphi_0}{\partial n}$, obtained as a projection of the boundary current of the resonance eigenfunction φ_0 onto the entrance subspace E_-^Λ of the closed channels. Then, omitting the factors $|K_-|^{-1/2}$ we may arrange the summands according to the decomposition

$$\mathcal{DN} = \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0 \rangle \langle \phi_0}{\lambda - \lambda_0^0} + \sum_{s \neq 0} \frac{1}{(2\mu_\Omega)^2} \frac{\phi_s \rangle \langle \phi_s}{\lambda - \lambda_s^0} := \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0 \rangle \langle \phi_0}{\lambda - \lambda_0^0} + \mathcal{K}_0,$$

where \mathcal{K}_0 is the contribution to \mathcal{DN} from the non-resonance eigenvalues $\lambda_s^0 \neq \lambda_0^0$. The norm of the contribution \mathcal{K}_0 , as an operator from $W_2^{3/2-\epsilon}$ to $W_2^{1/2-\epsilon}$ (for each $\epsilon > 0$), may be estimated by the spacing $\rho(\lambda_0)$ at the resonance level $\lambda_0 \approx \Lambda$. We explore the invertibility of the denominator $\mathbf{D}(\lambda)$ in two special cases : for shrinking networks and for thin networks, see comments below.

Lemma III.1 *If the wires are shrinking as $y \rightarrow \frac{y'}{\varepsilon^\omega}$ and the quantum wells are shrinking as $x \rightarrow \frac{x'}{\varepsilon_\Omega}$, but the Fermi level is kept constant during the shrinking, then the norm of the operator $K_-^{-1} \mathcal{K}$ on functions of the variables x', y' is estimated in $L_2(\Gamma)$ as*

$$\| K_-^{-1} \mathcal{K}_0 \| \leq C_0 \left(\frac{\varepsilon^\omega}{\varepsilon_\Omega} \right)^2. \quad (10)$$

Proof Notice that in course of shrinking the role of the resonance eigenvalue is being played by various eigenvalues of the Schrödinger operator on the quantum well. Generically the resonance eigenvalue is simple and the operator $K_-^{-1} \mathcal{K}_0$ is a bounded operator at the resonance value of the spectral parameter. Since the DN-map is homogeneous of degree -1 and $K_-^\Lambda = K_-$ admits an estimate by ε_ω from above, see (12) below, the estimate of the non-resonance term is obvious if the distance of the corresponding eigenvalue λ_s from the Fermi level E_Λ remains strictly positive in course of shrinking. This gives the required estimate of the contribution from all non-resonance terms with eigenvalues which do not approach the Fermi level E_Λ in the course of the shrinking. The number of others non-resonance terms, which correspond to eigenvalues approaching the Fermi level in course of shrinking, is finite. It is sufficient to estimate the contribution from a single non-resonance term. Consider the term which corresponds to the eigenvalue $\frac{\lambda_1}{\varepsilon_\Omega}$ closest to the resonance eigenvalue $\lambda_0' = \frac{\lambda_0}{\varepsilon_\Omega^2} \approx \Lambda$. Notice first that the shrinking of the normalized eigenfunction φ_1 of the dimensionless Schrödinger operator is described by the formula

$$\varphi_1'(x') = \frac{\varphi_1\left(\frac{x'}{\varepsilon_\Omega}\right)}{\left[\int_{\Omega'} |\varphi_1|^2\left(\frac{x'}{\varepsilon_\Omega}\right) dx'\right]^{1/2}} \approx \varphi_1\left(\frac{x'}{\varepsilon_\Omega}\right) \varepsilon_\Omega^{-1}.$$

Then the normal derivative of the shrinking eigenfunction is transformed as

$$\frac{\partial \varphi_1'}{\partial n} = \frac{\partial \varphi_1}{\partial n} \frac{1}{\varepsilon_\Omega^2}.$$

If the Fermi-level Λ is kept constant in course of shrinking, then the closest to the Fermi-level resonance eigenvalue is shifted to the spectral point $\lambda_0' \approx \Lambda \varepsilon_\Omega^2$ of the “dimensionless” operator, with λ_0' dimension $[\text{mass}]^{-1}$. Then the spacing $\rho'(\Lambda)$ on the resonance level is calculated as $\frac{\rho(E_\Lambda \varepsilon_\Omega^2)}{\varepsilon_\Omega^2}$. The projection P_E is presented via multiplication by the indicator of the bottom-section, and the norm of it is homogeneous first degree, hence proportional to δ^ω . Combining all these facts we obtain the following estimate for the contribution to the

DN-map from on the resonance lever from a single non-resonance term

$$\left\| \frac{P_E \frac{\partial \varphi'_1}{\partial n}}{\lambda'_1 - \lambda'_0} \right\| \leq \frac{\sup_{\Gamma} |\nabla \varphi|^2}{\rho(\Lambda \varepsilon_\Omega^2)} \frac{\varepsilon_\omega}{\varepsilon_\Omega^2}. \quad (11)$$

This result is in full agreement with the fact that the DN-map is homogeneous of order -1 . Then we have $\| \mathcal{K}_0 \| \leq C \frac{\varepsilon_\omega}{\varepsilon_\Omega^2}$.

One can easily obtain the estimate for $K_-(\lambda)$ at the Fermi-level:

$$\| (K_-(\lambda))^{-1} \| \approx \max_m \sqrt{\frac{\mu_m^\perp}{\mu_m^\parallel}} \frac{\varepsilon_\omega}{\pi} \quad (12)$$

if $2\mu_m^\perp (\varepsilon_\omega)^2 \max_m |E_\Lambda - V_m| < \pi$. Summarizing the estimates (11,12) we obtain the announced statement.

Remark Introducing the positive operator $|K_-| := -K_-$ one can derive a similar estimate in symmetrized form:

$$\| |K_-|^{-1/2} \mathcal{K}_0 |K_-|^{-1/2} \| \leq C_0 \left(\frac{\varepsilon_\omega}{\varepsilon_\Omega} \right)^2$$

with some constant C_0 .

The shrinking of the network, with the constant Fermi level Λ , can be applied to each quantum well and each quantum wire separately. Then the DN map on the joining of the wells is a direct sum of the DN-maps of quantum wells Ω_t , $t = 1, 2, \dots$, which implies:

$$\| \mathcal{K}_0 \| < \max_s \frac{\sup_{\Gamma} |\nabla \varphi_s|^2}{\rho(\Lambda \varepsilon_\Omega^2)} \frac{\varepsilon_\omega}{\varepsilon_\Omega^2},$$

and

$$\| |K_-|^{-1/2} \mathcal{K}_0 |K_-|^{-1/2} \| \leq \max_{s,m} \sqrt{\frac{\mu_m^\perp}{\mu_m^\parallel}} \frac{\sup_{\Gamma} |\nabla \varphi_s|^2}{\pi \rho(\Lambda \varepsilon_\Omega^2)} \left(\frac{\varepsilon_\omega}{\varepsilon_\Omega} \right)^2 := C_0 \left(\frac{\varepsilon_\omega}{\varepsilon_\Omega} \right)^2, \quad (13)$$

with an absolute constant C_0 depending on the shape of the network. If the shrinking of details of the network (the finite and infinite wires and vertex domains) is independent, then max in the preceding formula is taken over all contacting pairs of details Ω_t , ω^m and the maximal value of the ratio appears in the right side.

Definition We say that *the network is thin on the Fermi-level Λ* , if the condition $\| |K_-|^{-1/2} \mathcal{K}_0 |K_-|^{-1/2} \| < 1$ is fulfilled for resonance values of the spectral parameter near to the Fermi level: $\lambda \approx \Lambda$.

This condition is obviously fulfilled for shrinking networks, if $\frac{\varepsilon_\omega}{\varepsilon_\Omega} \ll 1$. But practically for given network and fixed Λ this condition can be also verified sometimes, based on direct calculations. In particular for the quantum switch [11] based a circular quantum well radius 1 with 4 quantum wires width δ attached to it (centered at the points $0, \pm \frac{2\pi}{3}, \pi$) the condition is fulfilled if $\delta < 1/2$, due to presence of some “natural” small parameter.

The following statement (Theorem 3.3) reveals the structure of singularities in the above representation (7) for thin (but non necessarily shrinking) networks.

To formulate and proof the statement we need more elaborated notations. Separate the resonance term in matrix elements of the DN-map of the operator L_0 presented as a matrix with respect to the basis E_\pm :

$$\begin{aligned} P_+^\Lambda (\mathcal{DN}) P_+^\Lambda &= \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^+ \langle \phi_0^+}{\lambda - \lambda_0^0} + \sum_{s \neq 0} \frac{1}{(2\mu_\Omega)^2} \frac{\hat{\phi}_s^+ \langle \hat{\phi}_s^+}{\lambda - \lambda_s^0} := \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^+ \langle \phi_0^+}{\lambda - \lambda_0^0} + \mathcal{K}_{++} \\ P_+^\Lambda (\mathcal{DN}) P_-^\Lambda &= \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^+ \langle \phi_0^-}{\lambda - \lambda_0^0} + \sum_{s \neq 0} \frac{1}{(2\mu_\Omega)^2} \frac{\phi_s^+ \langle \phi_s^-}{\lambda - \lambda_s^0} := \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^+ \langle \phi_0^-}{\lambda - \lambda_0^0} + \mathcal{K}_{+-} \\ P_-^\Lambda (\mathcal{DN}) P_+^\Lambda &= \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^+}{\lambda - \lambda_0^0} + \sum_{s \neq 0} \frac{1}{(2\mu_\Omega)^2} \frac{\phi_s^- \langle \phi_s^+}{\lambda - \lambda_s^0} := \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^+}{\lambda - \lambda_0^0} + \mathcal{K}_{-+} \end{aligned}$$

with $\mathcal{K}_{-+} = (\mathcal{K}_{+-})^+$, and

$$P_-^\Lambda (\mathcal{DN}) P_-^\Lambda = \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^-}{\lambda - \lambda_0^0} + \sum_{s \neq 0} \frac{\phi_s^- \langle \phi_s^-}{\lambda - \lambda_s^0} := \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^-}{\lambda - \lambda_0^0} + \mathcal{K}_{--}.$$

Here \mathcal{K}_{++} , \mathcal{K}_{\pm} , \mathcal{K}_{--} are the matrix elements of the contribution \mathcal{K}_0 to the DN-map from the non-resonance eigenvalues. The operators \mathcal{K}_{++} , \mathcal{K}_{+-} are bounded in $W_2^{3/2-0}(\Gamma)$, $\mathcal{K}_{-+} = \mathcal{K}_{+-}^+$ for real λ and \mathcal{K}_{--} acts from $W_2^{3/2-0}(\Gamma)$ into $W_2^{1/2-0}(\Gamma)$ the same way as K_- does. Then the expression (7) may be written as

$$\begin{aligned} \mathcal{DN}^\Lambda &= \frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^+ \langle \phi_0^+}{\lambda - \lambda_0^0} + \mathcal{K}_{++} + \\ &\left[\frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^+ \langle \phi_0^-}{\lambda - \lambda_0^0} + \mathcal{K}_{+-} \right] \frac{I}{\frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^-}{\lambda - \lambda_0^0} + \mathcal{K}_{--} - K_-} \left[\frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^+}{\lambda - \lambda_0^0} + \mathcal{K}_{-+} \right]. \end{aligned} \quad (14)$$

The positive operator $-K_- = |K_-|$ can be estimated from below by the distance from λ to the lowest upper threshold

$$\begin{aligned} \rho_-(\lambda) &= \min_{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m > \Lambda} \sqrt{2\mu_m^\parallel} \sqrt{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m - \lambda}, \\ \langle -K_- u, u \rangle &\geq \rho_- \|u\|_{L_2(\Gamma)}^2. \end{aligned}$$

Theorem III.3 *If the network is thin on the Fermi-level Λ , then the pole of the DN-map \mathcal{DN} at the simple resonance eigenvalue λ_0^0 of the operator L_0 on the compact part Ω_0 of the network (the singularity of the first addendum of (7)) is compensated by the pole of the second addendum and disappears as a singularity of the whole function \mathcal{DN}^Λ so that the whole expression (7) is regular at the point λ_0^0 . A new pole appears as a closest to Λ zero eigenvalue of the denominator $[P_-^\Lambda (\mathcal{DN}) P_-^\Lambda - K_-] \nu = 0$.*

Proof If the network is thin, $\| |K_-|^{-1/2} \mathcal{K}_0(\lambda_0) |K_-|^{-1/2} \| < 1$, then the operator

$$\mathcal{K}_{--} - K_- := k$$

is invertible: $k^{-1} = |K_-|^{-1/2} \left(1 - |K_-|^{-1/2} \mathcal{K}_{--} |K_-|^{-1/2} \right) |K_-|^{-1/2}$. Then the middle term of the above product (14) can be found as a solution of the equation

$$\left[\frac{1}{(2\mu_\Omega)^2} \frac{\phi_0^- \langle \phi_0^-}{\lambda - \lambda_0^0} + \mathcal{K}_{--} - K_- \right] u = f,$$

$$u = k^{-1} f - \frac{1}{\mathcal{D}} k^{-1} \phi_0^- \langle \phi_0^-, k^{-1} f \rangle,$$

where $\mathcal{D} = (2\mu_\Omega)^2 (\lambda - \lambda_0^0) + \langle \phi_0^-, k^{-1} \phi_0^- \rangle$. Zeroes of the function \mathcal{D} coincide with singularities of the middle term in the above formula (7) for the \mathcal{DN}^Λ and hence coincide with the eigenvalues of the intermediate operator L_Λ .

Substituting that expression into (14) we notice that all polar terms containing the factors $(\lambda - \lambda_0^0)^{-1}$ compensate each other so that the sum of them vanishes :

$$\begin{aligned} \mathcal{DN}^\Lambda &= \frac{1}{(2\mu_\Omega)^2} \frac{\phi^+ \langle \phi^+}{\lambda - \lambda_0} \left[1 - \frac{\langle \phi^-, k^{-1} \phi^- \rangle}{\lambda - \lambda_0} + \frac{1}{(2\mu_\Omega)^2} \frac{\langle \phi^-, k^{-1} \phi^- \rangle^2}{\mathcal{D}(\hat{\lambda} - \lambda_0)} \right] - \\ &\quad \frac{1}{(2\mu_\Omega)^2} \frac{\mathcal{K}_{+-} k^{-1} \phi^- \langle \phi^+}{\lambda - \lambda_0} \left[I - \frac{\langle \phi^-, k^{-1} \phi^- \rangle}{\mathcal{D}} \right] - \\ &\quad \frac{1}{(2\mu_\Omega)^2} \frac{\phi^+ \langle \mathcal{K}_{+-} k^{-1} \phi^-}{\lambda - \lambda_0} \left[I - \frac{\langle \phi^-, k^{-1} \phi^- \rangle}{\mathcal{D}} \right] + \\ &\quad \frac{1}{(2\mu_\Omega)^2} \frac{\mathcal{K}_{+-} k^{-1} \phi^- \langle \mathcal{K}_{+-} k^{-1} \phi^-}{\mathcal{D}} + \dots = \\ &\quad \frac{1}{(2\mu_\Omega)^2} \frac{\phi^+ - \mathcal{K}_{+-} k^{-1} \phi^- \langle \phi^+ - \mathcal{K}_{+-} k^{-1} \phi^-}{\mathcal{D}} + \dots, \end{aligned} \tag{15}$$

where the dots stay for terms defining the regular summand of \mathcal{DN}^Λ in a small neighborhood of the resonance.

Remark 1 One can see that on the first step of the approximation procedure we obtain the pole of \mathcal{DN}^Λ at the simple zero of the denominator \mathcal{D} with the same residue $\phi^+ \langle \phi^+$ as \mathcal{DN} , in full agreement with physical folklore. The residue, with a small correction obtained on the second step of the approximation procedure, is given by

$$\phi^+ - \mathcal{K}_{+-} k^{-1} \phi^- \langle \phi^+ - \mathcal{K}_{+-} k^{-1} \phi^-.$$

In particular this means that the portions $P_+ \frac{\partial \varphi_0^r}{\partial n}$ of resonance eigenfunctions of the intermediate operator L_Λ in the entrance subspace can be found via the successive approximation procedure (on the second step) as:

$$P_+ \frac{\partial \varphi_0^r}{\partial n} \approx \phi^+ - \mathcal{K}_{+-} k \phi^-,$$

if the network is thin. Similarly the shift of the resonance eigenvalue λ_0^0 to the zero λ_0^D of the denominator D

$$D(\lambda_0^D) = 0$$

can be estimated in first order of the approximation procedure as

$$\lambda_0^D = \lambda_0^0 - \frac{1}{(2\mu_\Omega)^2} \langle \varphi_0, |K_-|^{-1} \varphi_0 \rangle + \dots,$$

where the dots stay for terms estimated by powers of

$$\frac{1}{(2\mu_\Omega)^2} \langle \varphi_0, |K_-|^{-1/2} |\mathcal{K}_{--}| |K_-|^{-1/2} \varphi_0 \rangle$$

Remark 2 Note that the exponent K_- can be estimated from below in terms of the wave-number of the electron in the wires at the resonance energy λ_0^0

$$p_{min}(\lambda_0^0) = \min_{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} + V_m < \Lambda} \sqrt{2\mu_m^\parallel} \sqrt{\lambda_0 - \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m^2} - V_m}.$$

In case of thin networks the wave-number exceeds the contribution to the matrix element \mathcal{DN}_{--} of the DN-map of L_0 from the neighboring non-resonance eigenvalues.

The eigenvalues and the eigenfunctions of the discrete spectrum of the intermediate operator L_Λ can be found either by the minimizing of the corresponding Rayleigh ratio, or from the corresponding dispersion equation,

$$P_-^\Lambda (\mathcal{DN}) P_-^\Lambda - K_- \nu = 0$$

involving the DN-map of the Schrödinger operator L_0 with zero boundary condition on the border of the compact part Ω_0 of the network.

Theorem III.4 *The eigenvalues of the operator L_Λ may be found as vector zeroes (λ, ν_λ) of the dispersion equation*

$$\mathbf{D}(\lambda) \nu_\lambda = \mathcal{DN}_{--}(\lambda) \nu_\lambda - K_-(\lambda) \nu_\lambda = 0.$$

In particular for values of the spectral parameter between the maximal lower threshold λ_{max}^Λ and minimal upper threshold λ_{min}^Λ the dispersion equation takes the form

$$\nu = |K_-|^{-1/2} \mathcal{DN}_{--} |K_-|^{-1/2} \nu, \tag{16}$$

with the bounded operator-functions $|K_-|^{-1/2} \mathcal{DN}_{--} |K_-|^{-1/2}$ in $L_2(\Gamma)$. It may be transformed to an equation

$$\nu - \mathcal{D}(H, \lambda)\nu = 0,$$

with a trace class operator

$$\mathcal{D}(H, \lambda) := (H + \lambda)^2 \mathbf{k}^{-1/2} \mathcal{P}_H^+ \mathcal{R}_\lambda \mathcal{P}_H \mathbf{k}^{-1/2},$$

where

$$\mathbf{k} = \left[|K_-| + \mathcal{DN}_{--} (-H) - (H + \lambda) \mathcal{P}_H^+ \mathcal{P}_H \right] = \\ (|K_-|)^{1/2} \left[I + (|K_-|)^{-1/2} \left(\mathcal{DN}_{--} (-H) - (H + \lambda) \mathcal{P}_H^+ \mathcal{P}_H \right) (|K_-|)^{-1/2} \right] (|K_-|)^{1/2}$$

and \mathcal{R}_λ , \mathcal{P}_λ are respectively the resolvent and the Poisson map of the operator L on the compact part of the network with zero boundary condition. The corresponding scalar equation may be presented in the form

$$\det [I - \mathcal{D}(H, \lambda)] = 0. \quad (17)$$

Proof The projections $u_\Gamma \in E_-$ of the eigen-function u , $L_\Lambda u = \lambda u$ of the operator L_Λ onto the cross-sections Γ of the open channels should fulfill the condition $\frac{\partial u}{\partial n} \Big|_\Gamma = K_-^\Lambda(\lambda) u_\Gamma$. On the other hand the restrictions of u onto the compact part of the network fulfills the corresponding homogeneous equation, hence $\frac{\partial u}{\partial n} \Big|_\Gamma = \mathcal{DN}_{--}(\lambda)$. Matching both data with the boundary conditions (4) we obtain the dispersion equation:

$$K_-^\Lambda(\lambda) u_\Gamma = P_-^\Lambda \mathcal{DN} P_-^\Lambda(\lambda) u_\Gamma.$$

Due to the invertibility of $K_-^\Lambda(\lambda)$ below λ_{min}^Λ we obtain the first statement (16) of the theorem. The second statement requires the iterated Hilbert identity for the DN-map, see [68]:

$$\mathcal{DN}(\lambda) = \mathcal{DN}(-H) - (H + \lambda) \mathcal{P}_H^+ \mathcal{P}_H - (H + \lambda)^2 \mathcal{P}_H^+ \mathcal{R}_\lambda \mathcal{P}_H.$$

Both second and third terms of the sum in the right hand side are compact operators in $L_2(\Gamma)$, see the remark after the theorem 3.2, if the compact part Ω_0 of the network has a piecewise smooth boundary with Meixner boundary conditions at the inner corners. Moreover, the third term, after framing by factors K_-^Λ is an operator with a finite trace. Then the operator $\mathcal{D}(H, \lambda)$ has a finite trace too and the dispersion equation may be presented in form

$$\det [I - \mathcal{D}(H, \lambda)] = 0.$$

IV. SCATTERING MATRIX

In this section we rephrase some results of previous section in terms of Scattering Matrix and then derive and interpret the corresponding “one-pole approximation”.

Components of the Scattered waves of the Schrödinger operator \mathcal{L} in the lower channels on semi-infinite wires ω^m are presented by linear combination of modes: oscillating exponentials

combined with eigenfunctions of cross-sections in open channels and decreasing exponentials combined with corresponding eigenfunctions of cross-sections in closed channels:

$$\begin{aligned}
\psi_+ = & \sum_{\frac{\pi^2 l^2}{2\mu_m^\perp \delta_m} + V_m < \Lambda} e_l^m \nu_l^m e^{-i\sqrt{2\mu_m^\parallel} \sqrt{\lambda - V_m - \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m}} x} + \\
& \sum_{\frac{\pi^2 k^2}{2\mu_m^\perp \delta_m} + V_m < \Lambda} e_l^m S_{m,n}^{l,k} \nu_k^n e^{i\sqrt{2\mu_m^\parallel} \sqrt{\lambda - V_m - \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m}} x} + \\
& \sum_{\frac{\pi^2 k^2}{2\mu_m^\perp \delta_m} + V_m > \Lambda} e_l^m s_{m,n}^{l,k} \nu_k^n e^{-\sqrt{2\mu_m^\parallel} \sqrt{V_m + \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m} - \lambda} x}, \tag{18}
\end{aligned}$$

where ν_l^m are the components of the incoming plane wave, and the finite matrix $S = \{S_{m,n}^{l,k}\}$ is a Scattering matrix—the main object of our search. We present the above Scattering Ansatz in the following short form (19) introducing the notations: $\sum_{ml} e_l^m \nu_m^l = \nu_+ \in E_+$, $\{S_{m,n}^{l,k}\} = \mathbf{S}$, $\{s_{m,n}^{l,k}\} = \mathbf{s}$ and the diagonal matrices in E_+^Λ , E_-^Λ :

$$K_+ = \left\{ \sqrt{2\mu_m^\parallel} \sqrt{\lambda - V_m - \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m}} \right\}$$

for $\frac{\pi^2 k^2}{2\mu_m^\perp \delta_m} + V_m < \Lambda$ and

$$K_- = - \left\{ \sqrt{2\mu_m^\parallel} \sqrt{V_m + \frac{\pi^2 l^2}{2\mu_m^\perp \delta_m} - \lambda} \right\}$$

for $\frac{\pi^2 k^2}{2\mu_m^\perp \delta_m} + V_m > \Lambda$, then the Scattering Ansatz in the wires is:

$$\psi_+ := e^{-iK_+ x} \nu_+ + e^{iK_+ x} \mathbf{S} \nu_+ + e^{K_- x} \mathbf{s} \nu_+. \tag{19}$$

To derive the formula for the Scattering matrix of the operator \mathcal{L} on the whole network Ω we should substitute the above Ansatz into the boundary conditions of matching with components ψ_Ω of the Scattering Ansatz on the vertex domains

$$P_\pm [\psi] |_\Gamma = 0, \quad P_\pm \left[\frac{\partial \psi}{\partial n} \right] |_\Gamma = 0, \tag{20}$$

where $[\psi] |_\Gamma = [\psi^\omega - \psi_\Omega] |_\Gamma$ and $[\frac{\partial \psi}{\partial n}] |_\Gamma = \left[\frac{1}{\mu^\parallel} \frac{\partial \psi^\omega}{\partial n} - \frac{1}{\mu_\Omega} \frac{\partial \psi_\Omega}{\partial n} \right] |_\Gamma$. The components $\left\{ \psi^\omega, \frac{\partial \psi^\omega}{\partial n} \right\}$ of the above Ansatz in the wires are obtained by straightforward differentiation. However, the corresponding connection between the values of the components $\left\{ \psi_\Omega, \frac{\partial \psi_\Omega}{\partial n} \right\}$ of the Ansatz in the vertex domains Ω_t is given by the DN-map:

$$\mathcal{DN} \psi_\Omega \Big|_\Gamma = \frac{1}{2\mu_\Omega} \frac{\partial \psi_\Omega}{\partial n} \Big|_\Gamma.$$

Combining these connections and using the boundary conditions (20), we obtain an equation for the undefined coefficients of the Ansatz (18).

In this section we follow this standard program assuming that the network consists of “extended” vertex domains constituting the compact part Ω_0 , see section 1, and several semi-infinite wires ω^m , $m = 1, 2, \dots$ width δ_m attached orthogonally to Ω_0 at the bottom sections γ_m , $\Gamma = \cup_m \gamma_m$. The potential $V(x)$ of the Schrödinger operator

$$Lu = -\Delta u + V(x)u$$

takes constant values V_m on the wires ω^m and is a real bounded measurable function on vertex domains. Assume that the DN-map of the operator l_0 on each vertex domain, and hence on Ω_0 is already constructed and presented (formally) by the spectral series in terms of the eigenfunctions φ_r and eigenvalues λ_r corresponding to zero boundary conditions on $\partial\Omega_0$:

$$\mathcal{DN}(x, x') = \sum_s \frac{\frac{\partial \varphi_r(x)}{\partial n_x} \langle \frac{\partial \varphi_r(s)}{\partial n_{x'}} \rangle}{\lambda - \lambda_r^0}. \quad (21)$$

Here \mathcal{DN} is a direct sum of DN-maps of vertex domains. As a result of this steps, we obtain below the explicit formula for Scattering matrix in terms of matrix elements of \mathcal{DN} with respect to the orthogonal decomposition of the entrance subspace $E = E_+ \oplus E_-$, see (23).

On the other hand, choosing the Fermi level Λ we can define the intermediate operator L_Λ and construct the corresponding DN-map \mathcal{DN}^Λ as described in the previous section. This object is more sophisticate, because it already contains an information on closed channels, where the partial matching is already achieved. Really in second case we calculate Scattering solutions of the operator L matching limit values on real axis of the spectral parameter λ of square-integrable solutions of homogeneous intermediate equations with boundary data from E_+ on Γ - with Scattering Ansatz in open challels only:

$$\psi^\omega = e^{-iK_+x}\nu + e^{iK_+x}\mathbf{S}\nu. \quad (22)$$

The boundary data of the solution of the intermediate equation are connected via the corresponding (intermediate) DN-map:

$$\mathcal{DN}^\Lambda \psi_0 \Big|_\Gamma = \frac{1}{2\mu_m} P_+ \frac{\partial \psi_0}{\partial n} \Big|_\Gamma.$$

Assuming that $\nu = \sum_{m,l} \nu_{ml} e_l^m \in E_+$ we obtain from the matching conditions the following equation:

$$\mathcal{DN}^\Lambda [I + S] = [-iK_+ + iK_+ S]$$

and the corresponding representation for the Scattering matrix, see below (24). Summarizing two approaches to calculation of the Scattering matrix, described above, we obtain the following statement:

Theorem IV.1 *The following two formulae are valid for the Scattering matrix on the Network:*

a. The formula in terms of the standard DN-map \mathcal{DN} of the operator L_0 on the compact part Ω_0 of the network:

$$S(\lambda) = -\frac{(\mathcal{DN})_{++} - (\mathcal{DN})_{+-} \frac{I}{(\mathcal{DN})_{--} - K_-} (\mathcal{DN})_{-+} + iK_+}{(\mathcal{DN})_{++} - (\mathcal{DN})_{+-} \frac{I}{(\mathcal{DN})_{--} - K_-} (\mathcal{DN})_{-+} - iK_+}, \quad (23)$$

and

b. The formula for Scattering matrix in terms of the DN-map \mathcal{DN}^Λ of the intermediate operator:

$$\mathbf{S}(\lambda) = -\frac{\mathcal{DN}^\Lambda + iK_+}{\mathcal{DN}^\Lambda - iK_+}. \quad (24)$$

In both formulae the denominator is the first factor of the product.

Note that both above formulae are equivalent due to connection between the DN-maps of the intermediate operator and DN-map of Dirichlet problem on the compact part of the network, established in previous section. Though the formula (24) contains more sophisticated object \mathcal{DN}^Λ compared with \mathcal{DN} , it may be more convenient for calculating resonances, see [59], and for the description of transition processes, because the Scattering matrix is presented as a combination of bounded operators.

One can notice that leading terms in the numerator and denominator of the above expression (24) for the Scattering matrix near the resonance eigenvalue λ_0 are : the polar term

$$\frac{P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \rangle \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s}}{\lambda - \lambda_0^\Lambda} := \frac{\phi_0(x) \rangle \langle \phi_0(s)}{\lambda - \lambda_0^\Lambda}$$

and $iK_+(\lambda)$, which is estimated from below on the spectral band $\Delta_\Lambda = [\lambda_{max}^\Lambda, \lambda_{min}^\Lambda]$:

$$\left| K_+^{-1}(\lambda) \right| \leq \frac{1}{\sqrt{2\mu_m} \sqrt{\lambda - \lambda_{max}^\Lambda}} := \frac{1}{\mathbf{k}}. \quad (25)$$

Assume that the remaining non-resonance part of DN-map

$$\left[\mathcal{DN}^\Lambda - \frac{P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \rangle \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s}}{\lambda - \lambda_0^\Lambda} \right] := \mathcal{DN}_0^\Lambda$$

is subordinated to iK_+ in a small real neighborhood $(\lambda_0 - \varepsilon, \lambda_0 + \varepsilon) := \Delta_\varepsilon$ of the resonance eigenvalue, that is : the operator $K_+^{-1/2} \mathcal{DN}_0^\Lambda K_+^{-1/2} = \mathbf{K}$ is estimated as

$$|\mathbf{K}| = \left| K_+^{-1/2} \mathcal{DN}_0^\Lambda K_+^{-1/2} \right| \leq d < 1, \quad (26)$$

on thin or shrinking network, with $d = d(\varepsilon)$. This, in particular, means that the spacing on the resonance level is large comparing with ε . Note that, due to analyticity of both functions K_+ , \mathcal{DN}_0^Λ at the resonance level the above subordination condition (26) can be extended to some complex neighborhood U_ε^C of the resonance eigenvalue λ_0^Λ

Form the unitary on real axis λ combination of the leading terms in the numerator and denominator

$$S_0(\lambda) = \frac{iK_+ + \frac{\phi_0 \langle \phi_0 \rangle}{\lambda - \lambda_0^\Lambda}}{iK_+ - \frac{\phi_0 \langle \phi_0 \rangle}{\lambda - \lambda_0^\Lambda}}. \quad (27)$$

Under certain conditions this combination may serve a “one-pole approximation ” of the Scattering matrix near the resonance eigenvalue. Zeroes of S_0 sit in upper half-plane and can be found from the algebraic equation $\lambda = \lambda_0^\Lambda + i\langle K_+^{-1}(\lambda) \phi_0, \phi_0 \rangle$. If

$$|\langle K_+ \phi_0, \phi_0 \rangle| < \varepsilon_1, \text{ and } |\langle K'_+ \phi_0, \phi_0 \rangle| \leq q, \quad \frac{\varepsilon_1}{1-q} < 1, \quad (28)$$

then a single zero of it sits in the above complex neighborhood U_ε^C and it can be found by successive approximations procedure.

Theorem IV.2 *If both conditions (26,28) are fulfilled, with d small enough, then on the some real neighborhood U_ε^R of the resonance eigenvalue the following estimate is true*

$$\sup_{\lambda \in U_\varepsilon^R} |S(\lambda) - S_0(\lambda)| \leq \frac{2d}{1-d} \frac{3}{2} |K_+^{1/2}(\lambda_0^\Lambda)| |K_+^{-1/2}(\lambda_0^\Lambda)|, \quad (29)$$

and there exist a single zero of a Scattering matrix near to the above zero of a one-pole approximation.

Proof. With notations introduced above the expression (24) can be presented on Δ_ε as

$$\begin{aligned} S_0(\lambda) &= \frac{iK_+ + \frac{\phi_0 \langle \phi_0 \rangle}{\lambda - \lambda_0^\Lambda} + \mathcal{DN}_0^\Lambda}{iK_+ - \frac{\phi_0 \langle \phi_0 \rangle}{\lambda - \lambda_0^\Lambda} - \mathcal{DN}_0^\Lambda} = \\ &= K_+^{-1/2} \frac{iI_+ + \frac{K_+^{-1/2} \phi_0 \langle K_+^{-1/2} \phi_0 \rangle}{\lambda - \lambda_0^\Lambda} + \mathbf{K}}{iI_+ - \frac{K_+^{-1/2} \phi_0 \langle K_+^{-1/2} \phi_0 \rangle}{\lambda - \lambda_0^\Lambda} - \mathbf{K}} K_+^{1/2}, \end{aligned} \quad (30)$$

with $\mathbf{K} = K_+^{-1/2} \mathcal{DN}_0^\Lambda K_+^{-1/2}$, $|\mathbf{K}| = d$. The formula (27) can be presented in a similar form

$$S_0(\lambda) = K_+^{-1/2} \frac{iI_+ + \frac{K_+^{-1/2} \phi_0 \langle K_+^{-1/2} \phi_0 \rangle}{\lambda - \lambda_0^\Lambda}}{iI_+ - \frac{K_+^{-1/2} \phi_0 \langle K_+^{-1/2} \phi_0 \rangle}{\lambda - \lambda_0^\Lambda}} K_+^{1/2} := K_+^{-1/2} \frac{D_+(\lambda)}{D_-(\lambda)} K_+^{1/2}. \quad (31)$$

Then

$$\begin{aligned} S(\lambda) - S_0(\lambda) &= \\ K_+^{-1/2} \frac{1}{D_-(\lambda)} \left[\frac{\mathbf{K}}{I_+ - \mathbf{K}D_-^{-1}} \right] (D_+^{-1} - D_-^{-1}) D_+(\lambda) K_+^{1/2}. \end{aligned} \quad (32)$$

In above real neighborhood the whole expression is small if \mathbf{K} is small. Really, denoting $\psi = K_+^{-1/2} \phi_0$ and denoting by P_ψ the corresponding orthogonal projection, $P_\psi^\perp = P_+ - P_\psi$, we have :

$$D_\pm^{-1} = P_\psi^\perp + P_\psi \frac{1}{i \pm \frac{\langle K_+^{-1} \phi_0, \phi_0 \rangle}{\lambda - \lambda_0^\Lambda}},$$

$$D_+^{-1} - D_-^{-1} = \frac{2\langle K_+^{-1} \phi_0, \phi_0 \rangle (\lambda - \lambda_0^\Lambda)}{\langle K_+^{-1} \phi_0, \phi_0 \rangle^2 + (\lambda - \lambda_0^\Lambda)^2} P_\psi$$

$$(D_+^{-1} - D_-^{-1}) D_+ = \frac{2\langle K_+^{-1} \phi_0, \phi_0 \rangle}{\langle K_+^{-1} \phi_0, \phi_0 \rangle - i(\lambda - \lambda_0^\Lambda)} P_\psi$$

In particular on real neighborhood $|D_\pm^{-1}| \leq 1$, $|D_+^{-1} - D_-^{-1}| \leq 1$, $|(D_+^{-1} - D_-^{-1}) D_+| \leq 2$ and $\left| \left[I - \mathbf{K} D_-^{-1} \right]^{-1} \right| < \frac{1}{1-d}$, hence on real axis we have the estimation of the inner bracket in (32) by $\frac{d}{1-d}$ and the estimation of the difference (32) on the real neighborhood Δ_ε

$$|S - S_0| < \frac{d}{1-d} \sup_{\lambda \in \Delta_\varepsilon} |K_+^{1/2}(\lambda)| \sup_{\lambda \in \Delta_\varepsilon} |K_+^{-1/2}(\lambda)|. \quad (33)$$

For small q and hence small ε , the above estimate can be replaced by the

$$|S - S_0| < \frac{d}{1-d} B |K_+^{1/2}(\lambda_0^\Lambda)| |K_+^{-1/2}(\lambda_0^\Lambda)|,$$

with some coefficient B greater then 1, for instance $B = 3/2$. Similar estimation may be obtained inside the corresponding complex neighborhood U_ε^C on the small circle C_ε centered at the single zero $\lambda_0 = \lambda_0^\Lambda + i\langle K_+(\lambda_0)\phi_0, \phi_0 \rangle$ of S_0 , with radius equal $|\langle K_+(\lambda_0)\phi_0, \phi_0 \rangle|$. Then we have similar estimate,

$$|S - S_0| \Big|_{C_\varepsilon} < \frac{2d}{1-d} \sup_{\lambda \in C_\varepsilon} |K_+^{1/2}(\lambda)| \sup_{\lambda \in C_\varepsilon} |K_+^{-1/2}(\lambda_0^\Lambda)| \approx$$

$$\frac{2d}{1-d} B |K_+^{1/2}(\lambda_0^\Lambda)| |K_+^{-1/2}(\lambda_0^\Lambda)| \quad (34)$$

where we replaced maximal values of norms on the circle by values of norms at the resonance eigenvalue λ_0^Λ , assuming that ε is small. If the condition

$$\frac{2d}{1-d} B |K_+^{1/2}(\lambda_0^\Lambda)| |K_+^{-1/2}(\lambda_0^\Lambda)| < 1$$

is fulfilled, then there exist, due to the operator version of Rouchet theorem,[36], an isolated zero of the Scattering matrix inside the circle C_ε .

Summarizing results obtained in actual and previous sections we see that the step-wise structure of continuous spectrum on the quantum network permits us to reduce calculation of the Scattering matrix on the spectral band $\Delta_\Lambda = [\lambda_{max}^\Lambda, \lambda_{min}^\Lambda]$ to matching solutions in

neighboring domains via proper Dirichlet-to-Neumann map. Hence the large-time asymptotic of corresponding non-stationary processes is defined by the shape of eigenfunctions of discrete spectrum of the intermediate operator. One can use the variational method for the construction both the eigenfunctions and eigenvalues of the intermediate operator below the threshold λ_{\min}^{Λ} , and thus obtain the Scattering matrix from the solution of the variational problem.

The derived estimation of the deviation of the one-pole approximation from the Scattering matrix and the estimation of positions of corresponding resonances are too crude. The following “physical” motivation shows, that possibly contribution from some non-resonance eigenvalues and from the continuous spectrum in the previous expression (24) for the Scattering matrix may be neglected under much wider conditions. This motivation shows that the one-pole, or possibly few-pole approximations, may give a reasonably complete physical picture of dynamical processes on the network.

Assume that Λ is the Fermi level in the wires and T is properly scaled temperature. Then one may obtain an approximate expression for the Scattering matrix in an essential interval $(\Lambda - T, \Lambda + T)$ of energy by substituting into (24) properly reduced expression for the DN-map \mathcal{DN}_T^{Λ} containing singularities only in that interval. Really, one usually estimate the number of excited modes in Fermi-systems with discrete spectrum, considering the corresponding essential interval, because dynamics of electrons outside the interval is suppressed due to the Fermi distribution. We just extend this principle to the case when continuous spectrum is present, and implement it via replacing of the DN-map of the intermediate operator by the “essential part” of it :

$$\begin{aligned} \mathcal{DN}^{\Lambda} \rightarrow \mathcal{DN}_T^{\Lambda}(\lambda) = \frac{1}{(2\mu_{\Omega})^2} \sum_{(\Lambda-T < \lambda_r^{\Lambda} < \Lambda+T)} \frac{P_+ \frac{\partial \varphi_r(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_r(s)}{\partial n_r} \rangle}{\lambda - \lambda_r^{\Lambda}} + \\ \sum_{V_m + \frac{\pi^2 l^2}{2\mu_m \delta_m^2} > \Lambda} \frac{1}{(2\mu_{\Omega})^2} \int_{(\Lambda-T < \rho < \Lambda+T)} \frac{P_+ \frac{\partial \varphi_{\rho,l}(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_{\rho,l}(s)}{\partial n_s} \rangle}{\lambda - \rho} d\rho. \end{aligned} \quad (35)$$

Substituting the the essential part of the DN-map into the expression (24) we obtain the corresponding “dynamical approximation” for the Scattering matrix on the essential interval of energy:

$$S(\lambda) \approx -\frac{\mathcal{DN}_T^{\Lambda} + iK_+}{\mathcal{DN}_T^{\Lambda} - iK_+}. \quad (36)$$

The reduced *essential* part \mathcal{DN}_T^{Λ} of the Dirichlet-to-Neumann map of the intermediate operator may contain one or several polar terms and an integral on an interval of the continuous spectrum. We will consider in further text the case when the essential interval does not overlap with continuous spectrum of the intermediate operator $\Lambda + T < \lambda_{\min}^{\Lambda}$ and neglect the integral on the continuous spectrum. We call the essential interval of energy $[\Lambda - T, \Lambda + T]$ an *essential spectral band* and denote it by Δ_{Λ}^T . One may assume, that for narrow wires the continuous spectrum does not overlap with essential spectral band. The resulting *essential* expression (36) for the Scattering matrix is actually a Scattering matrix of some solvable

model, similar to one constructed in [13, 32, 72]. In particular we again obtain the “one-pole approximation” (1) for the Scattering matrix near the resonance

$$S(\lambda) = -\frac{\mathcal{DN}^\Lambda + iK_+}{\mathcal{DN}^\Lambda - iK_+} \approx -\frac{\frac{P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s} \rangle}{\lambda - \lambda_0^\Lambda} + iK_+(\lambda)}{\frac{P_+ \frac{\partial \varphi_0(x)}{\partial n_x} \langle P_+ \frac{\partial \varphi_0(s)}{\partial n_s} \rangle}{\lambda - \lambda_0^\Lambda} - iK_+(\lambda)},$$

if only one resonance eigenvalue $\lambda_0^\Lambda \approx \Lambda$ of the the intermediate operator is sitting on the essential spectral band Δ_Λ^T .

V. STAR-SHAPE MODEL OF A QUANTUM NETWORK

The aim of this section is: to construct a solvable model for general Quantum network with a finite number of semi-infinite wires. The model network will be constructed of a single vertex, where the essential part of the intermediate operator is substituted by some finite-dimensional operator, and several quasi-one-dimensional quantum wires attached to it, emulating the open channels. We will choose the parameters of the model such that the corresponding Scattering matrix will coincide with the essential Scattering matrix of the Quantum Network (36). Similar construction for the simplest Quantum Network - a three-terminal Quantum Switch - was developed in preprint [64], see Fig.1 below. We will use in this section notations similar to ones introduced in section 2

$$U_\Omega = \sum_t \oplus u_{\Omega_t}, \quad U^\omega = \sum_{t,m} \oplus u_{t,m}^\omega,$$

but we assume now that vector functions U_Ω, U^ω present elements of functional spaces not on the bottom sections of channels, but on the vertex domains and wires respectively. With these notations we can present the basic Schrödinger equation on the vertex domains and on the wires in symbolic form

$$\begin{aligned} -\frac{1}{\mu_\Omega} \Delta U_\Omega + V_\Omega U_\Omega &= E U_\Omega \\ -\frac{1}{\mu^\parallel} \frac{\partial^2 U^\omega}{\partial x^2} + \frac{1}{\mu^\perp} \frac{\partial^2 U^\omega}{\partial y^2} + V^\omega U^\omega &= E U^\omega, \end{aligned} \quad (37)$$

with a bounded measurable potentials $V_\Omega = \{V_t\}$ on the wells and constant potentials $V^\omega = \{V_m\}$ on the wires. Consider the the entrance eigen-vectors e_l^m of cross-section and corresponding orthogonal projections p_l^m in spaces of square-integrable functions on bottom sections of the wires ω^m , see section 2, and form the entrance subspaces E_\pm for open and closed channels with corresponding projections

$$P_\pm = \sum_{\pm} \oplus p_l^m, \quad \dim E_+ = N$$

with summation over the thresholds below and above the Fermi level Λ respectively. For instance: we take for E_+ the sum of all p_l^m with indices satisfying the condition

$\frac{1}{2\mu_{\perp m}} \frac{\pi^2 l^2}{\delta_m^2} + V_m < \Lambda$ for E_+ . For values of the spectral parameter on the minimal spectral band $[\lambda_{min}^L, \lambda_{max}^L]$ containing the Fermi level Λ , we introduce an operator-valued Wave-number \mathbf{P}_+ for open channels as a positive square root from

$$\mathbf{P}_+^2 = \sum_{\{+\}} \left\{ \lambda - \frac{1}{2\mu_{\perp m}} \frac{\pi^2 l^2}{\delta_m^2} - V_m \right\} p_l^m := \lambda - \mathbf{V}^\omega,$$

with summation $\{+\}$ over all open channels, and the positive decrement P_- for closed channels:

$$\mathbf{P}_-^2 = \sum_{\{-\}} \left\{ \frac{1}{2\mu_{\perp m}} \frac{\pi^2 l^2}{\delta_m^2} + V_m - \lambda \right\} p_l^m = \mathbf{V}^\omega - \lambda.$$

The introduced operators are connected with operators K_{\pm} from the previous section

$$K_{\pm} = \sqrt{2\mu^{\parallel}} \mathbf{P}_{\pm}.$$

Corresponding exponential solutions of the Schrödinger equation in the wires are:

$$e^{\pm i K_+ x} e, \text{ with } e \in E_+, \text{ and } e^{\pm i K_- x}, e \text{ with } e \in E_-.$$

Depending on architecture of the Quantum Network one may construct the intermediate operator either blocking open channels in *all wires*, as suggested at the end of section 2, or blocking open channels only in *semi-infinite wires*. When constructing the solvable model of the network we also have a choice: either we present the whole network as a single star-shaped graph with a single resonance vertex, or as a joining of star-shaped graphs with resonance vertices, connected by finite quantum wires. In second case the parameters of the finite wires enter the model as explicit parameters. We guess that the second representation is more convenient for detailed engineering analysis of networks and especially for optimization of their transport properties. Nevertheless we choose now the former construction, firstly: as more elementary and, secondly: just to include in our construction non-trivial (bent of periodic) internal finite wires. When analysis of the first construction is done, we can, at least in principle, develop analysis for the second one, with straight connecting wires, in algebraic way, based on star-shaped elements. Note that importance of star-shaped elements was noticed long ago and remains motivation of numerous recent papers, see for instance [26, 39]. We prove here that the star-shaped graph with a “resonance vertex”, see our construction below, is an universal object in spectral theory of Quantum Graphs .

When chopping off the open channels in semi-infinite wires only, we obtain a self-adjoint intermediate operator L_{Λ} and construct the corresponding DN-map \mathcal{DN}^{Λ} and the approximation of the Scattering matrix on the essential spectral band, (36). The corresponding Scattering Ansatz (22) in semi-infinite open channels satisfies the equation

$$-\frac{1}{\mu^{\perp}} \frac{d^2 U^{\omega}}{dx^2} + \mathbf{V}^{\omega} U^{\omega} = \lambda U^{\omega}. \quad (38)$$

We choose the outer (“trivial”) the part of the model - in open channels - in form of original matrix Schrödinger operator

$$l U^\omega = -\frac{1}{\mu^\perp} \frac{d^2 U^\omega}{dx^2} + \mathbf{V}^\omega U^\omega$$

in $L_2(E, [0, \infty))$ and we will use the same Scattering Ansatz (22) in open wires as for the original problem. But the construction of the vertex part of the model will be done with a major change of the original intermediate operator.

Based on the above physical motivation we assume that only a finite number N_T of eigenvalues of the intermediate operator sits on the essential spectral band and no change of multiplicity of the continuous spectrum occurs. Then we will substitute the intermediate operator on the Network by some finite-dimensional positive hermitian matrix A acting in an abstract space E_A , $\dim E_A = N_T$. The eigenvalues and normalized eigenvectors of the operator A will be denoted by k_s^2 , e_s correspondingly, $s = 1, 2, \dots, N_T$. The eigenvalues and the boundary parameters of the model β , see below (43), will be defined later based on comparison of the Scattering matrix of the model with the essential Scattering matrix. The resulting operator \mathbf{A}_β we obtain is a simplest star-shaped model of the Quantum network with the compact part substituted by a sophisticate Quantum Dot. In our construction we follow the receipt of construction of zero-range potentials with inner structure described in [6, 70], see also references therein.




FIG. 1: Three-terminal Quantum Switch

The corresponding model for the three-terminal Quantum Switch is used in [10] for estimation of the parameter regime of the switch.

Restrict both l and A to symmetric operators onto the corresponding domains: $l \rightarrow l_0 = l \Big|_{D_0^l}$ defined on functions vanishing near $x = 0$; the operator is restricted $A \rightarrow A_0 = A \Big|_{D_0^A}$ such that given subspace $N \in E_A$ would play the role of deficiency subspace at the spectral point $i : N = N_i$, $\dim N = d$. Then dual deficiency subspace is $N_{-i} = \frac{A+iI}{A-iI} N$. Define the domain of the restricted operator A_0 as $D_0^A = \frac{I}{A-iI} [E_A \ominus N_i]$ of A_0 . It is not

dense, since A is bounded. Nevertheless, under condition that the deficiency subspaces $N_{\pm} = N_{\pm i}$ do not have common elements, see for instance [53, 57], the extension procedure for the orthogonal sum $l_0 \oplus A_0$ can be developed with use of the symplectic formalism, see for instance [72]. The case $\dim E_A = 1$ is not formally covered by the above condition, but the corresponding extension also was constructed in [87, 88] and the relevant formulae for the scattering matrix and scattered waves remain true. The extension of the restricted operator \mathbf{A}_0 is reduced to selection of a Lagrangian plane of the sum of the corresponding boundary forms, see for instance [57, 70], and below, see 43, where the Lagrangian plane is chose based on proper boundary condition. The same description of extensions remains valid in case $\dim E_A = 1$. We will use this fact below, see 54.

The boundary form of the differential operator l_0^+ is obtained via standard integration by parts:

$$\mathcal{J}_l(U, V) = \langle l_0^+ U, V \rangle - \langle U, l_0^+ V \rangle = \langle U'(0), V(0) \rangle - \langle U(0), V'(0) \rangle, \quad (39)$$

where $U(0), V(0) \in E_+$ and the derivatives are taken in positive direction.

We assume that the Hermitian operator $A : E_A \rightarrow E_A$, $\dim E_A = N_T$, is defined by its spectral decomposition (on discrete spectrum)

$$A = \sum_s^{N_T} k_s^2 P_s,$$

where k_s^2 are positive eigenvalues and P_s are the corresponding spectral projections, $P_s = e_s \rangle \langle e_s$. Choose an ortho-normal basis in N_i $\{f_l\} = \{f_{l,i}\}$, $l = 1, 2, \dots, d$, $d = \dim N_i \leq N_T$, as a set of deficiency vectors of the restricted operator A_0 . Then vectors $\frac{A+iI}{A-iI} f_l$ form an ortho-normal basis in the dual deficiency subspace N_{-i} . We assume that the subspaces N_i and N_{-i} do not overlap, hence their (direct) sum $\mathcal{N} = N_i + N_{-i}$, - the *defect* of the operator A_0 , - has the dimension $2d = 2$. Under this assumption the deficiency index of the restricted operator A_0 is equal to (d, d) . The defect contains elements from the domain D_0 of A , so the restricted operator $A_0 = A|_{D_0}$ is not densely defined, and hence the adjoint operator does not exist. However, under the above condition one may use the formal adjoint A_0^+ defined on defect:

$$u = \sum_{l=1}^d [x_{l,i} e_{l,i} + x_{l,-i} e_{l,-i}] \in \mathcal{N},$$

by the von-Neumann formula, see for instance [35],

$$A_0^+ u = \sum_{l=1}^d [-i x_{l,i} f_{l,i} + i x_{l,-i} f_{l,-i}].$$

We will use the formal adjoint during the construction of extensions (see [53, 57]) since, for closed operators with the finite deficiency indices, the construction of the extension is actually developed in the defect. In order to use the symplectic version of the operator-extension techniques we introduce in the defect \mathcal{N} a new basis $w_{\pm,l}$, on which the formal adjoint A_0^+ is correctly defined due to the above assumption of non-overlapping:

$$w_{l,+} = \frac{f_{l,i} + f_{l,-i}}{2} = \frac{A}{A-iI} f_l, \quad w_{l,-} = \frac{f_{l,i} - f_{l,-i}}{2i} = -\frac{I}{A-iI} f_l,$$

$$A_0^+ w_{l,+} = w_{l,-}, \quad A_0^+ w_{l,-} = -w_{l,+}.$$

The following formula of integration by parts with abstract operators was proved in ([70, 72]):

Lemma V.1 *Consider elements from the domain of the (formal) adjoint operator A_0^+ :*

$$u = u_0 + \sum_l [\xi_{l,+}^u w_{l,+} + \xi_{l,-}^u w_{l,-}] = u_0 + \frac{A}{A - iI} \bar{\xi}_+^u - \frac{1}{A - iI} \bar{\xi}_-^u,$$

$$v = v_0 + \frac{A}{A - iI} \bar{\xi}_+^v - \frac{1}{A - iI} \bar{\xi}_-^v$$

with symplectic coordinates $\bar{\xi}_\pm^u, \bar{\xi}_\pm^v$:

$$\bar{\xi}_\pm^u = \sum_l \xi_{l,\pm}^u f_{l,i} \in N, \quad \bar{\xi}_\pm^v = \sum_l \xi_{l,\pm}^v f_{l,i} \in N.$$

Then, the boundary form of the formal adjoint operator is equal to

$$\mathcal{J}_A(u, v) = \langle A_0^+ u, v \rangle - \langle u, A_0^+ v \rangle = \langle \bar{\xi}_+^u, \bar{\xi}_-^v \rangle_N - \langle \bar{\xi}_-^u, \bar{\xi}_+^v \rangle_N. \quad (40)$$

The fundamental Krein formula [54, 65] for Generalized Resolvents of Symmetric Operators can be easily derived from the next statement proved in [70]. It helps to solve the non-homogeneous equations with the adjoint operator $(A_0^+ - \lambda I)u = f$. In our situation similar to [2] it is used in course of calculation of the scattering matrix, see below (44).

Lemma V.2 *The symplectic coordinates $\bar{\xi}_\pm^u \in N$ of the vector-valued function*

$$u = \frac{A + iI}{A - \lambda I} \bar{\xi}_+^u := u_0 + \frac{A}{A - iI} \bar{\xi}_+^u - \frac{1}{A - iI} \bar{\xi}_-^u, \quad (41)$$

which satisfies the adjoint equation $[A_0^+ - \lambda I]u = 0$, are connected by the formula

$$\bar{\xi}_-^u = -P_N \frac{I + \lambda A}{A - \lambda} \bar{\xi}_+^u \quad (42)$$

The operator-function

$$\mathcal{M} = P_N \frac{I + \lambda A}{A - \lambda I} P_N : N \rightarrow N,$$

with a positive imaginary part in the upper half-plane $\Im \lambda > 0$ coincides actually with “Q-function”, introduced by M. Krein ([54]). It serves an abstract analog of the celebrated function used by H. Weyl in course of construction of self-adjoint extensions of the second order differential operator of Schrödinger type, see, for instance [92], where the original construction by H. Weyl is presented. The operator-function \mathcal{M} exists almost everywhere on real axis λ and has a finite number of simple poles sitting at the eigenvalues k_l^2 of A . This function plays an important role in description of spectral properties of self-adjoint extensions of symmetric operators, see [38, 54, 72].

The boundary form $\mathbf{J}(\mathbf{U}, \mathbf{V})$ of the orthogonal sum $\mathbf{A}_0^+ = A_0^+ \oplus l_0^+$ of the restricted matrix and the differential operator on elements $(U, u) = \mathbf{U}$ on the orthogonal sum of the

corresponding spaces is calculated as a sum of the forms (39,40). The self-adjoint extensions of the corresponding operator $\mathbf{A}_0 = A_0 \oplus l_0$ are obtained as restrictions of the adjoint operator $\mathbf{A}_0^+ = A_0^+ \oplus l_0^+$ onto Lagrangian planes of the form $\mathbf{J}(\mathbf{U}, \mathbf{V})$. These planes may be defined by the boundary conditions connecting the symplectic coordinates $U'(0)$, $U(0)$, $\vec{\xi}_+^u$, $\vec{\xi}_-^u$ of components of the corresponding elements in the deficiency subspaces. For instance, one may select a d -dimensional operator $\beta : E \rightarrow \mathcal{E}$ and define the Lagrangian plane \mathbf{L}_β by the boundary condition

$$\begin{pmatrix} U'(0) \\ -\vec{\xi}_+ \end{pmatrix} = \begin{pmatrix} \beta_{00} & \beta_{01} \\ \beta_{01}^+ & 0 \end{pmatrix} \begin{pmatrix} U(0) \\ -\vec{\xi}_- \end{pmatrix}. \quad (43)$$

This condition defines a self-adjoint extension \mathbf{A}_β of the restricted operators $A_0 \oplus l_0$ in $L_2(R, E_+) \oplus E_A$. The absolutely continuous of the operator \mathbf{A}_β coincides with the spectrum of the exterior part of the model, hence - with the spectrum of the trivial component l_Λ of the split operator \mathcal{L}_Λ . The corresponding eigenfunctions of \mathbf{A}_β on the minimal spectral band $\lambda_{\max}^\Lambda \lambda_{\min}^\Lambda$ containing the Fermi-level can be found via substitution into above boundary condition the column combined of Anzatzes (22) and (41)

$$\Psi = \begin{pmatrix} e^{-iK_+x}\nu + e^{iK_+x}\mathbf{S}\nu \\ \frac{A+iI}{A-iI}\vec{\xi}_+^u \end{pmatrix}.$$

It gives the linear equation for Scattering matrix:

$$\begin{pmatrix} -iK_+(\nu - S\nu) \\ -\vec{\xi}_+ \end{pmatrix} = \begin{pmatrix} \beta_{00} & \beta_{01} \\ \beta_{00}^+ & 0 \end{pmatrix} \begin{pmatrix} \nu + S\nu \\ \mathcal{M}\vec{\xi}_+ \end{pmatrix}.$$

Solving this equation we can obtain the Scattered waves and the formula we needed:

Lemma V.3 *The Scattering matrix for the constructed model is an analytic function of the spectral parameter λ :*

$$\mathbf{S}(\lambda) = \frac{iK_+ + [\beta_{00} - \beta_{01}\mathcal{M}\beta_{10}]}{iK_+ - [\beta_{00} - \beta_{01}\mathcal{M}\beta_{10}]}, \quad (44)$$

with denominator of the fraction preceding the numerator.

Now we will choose the parameter β such that the operator-function $[\beta_{00} - \beta_{01}\mathcal{M}\beta_{10}]$ acting in E_+ coincides with the essential component \mathcal{DN}_T^Λ of the DN-map of the intermediate operator. Really, denote by Q_s the spectral projection onto the eigen-space of A corresponding to the eigenvalue k_s^2 framed by projections onto the deficiency subspace $N_i = N$

$$Q_s = P_i e_s \rangle \langle P_i e_s.$$

Then the above expression takes the form :

$$\begin{aligned} & [\beta_{00} - \beta_{01}\mathcal{M}\beta_{10}] = \\ & \left[\beta_{00} + \sum_{s=1}^{N_T} k_s^2 \beta_{01} Q_s \beta_{10} \right] + \sum_s \frac{1 + k_s^4}{k_s^2 - \lambda} \beta_{01} Q_s \beta_{10}. \end{aligned} \quad (45)$$

We will define the boundary parameters β_{10} , $\beta_{01} = \beta_{10}^+$ later, but once they are defined, we choose β_{00} such that the first summand in the right side of (45) vanishes: $\beta_{00} + \sum_s k_s^2 \beta_{01} Q_s \beta_{10} = 0$. Then the Scattering matrix take the form:

$$\mathbf{S}(k) = \frac{iK_+ - \sum_{s=1}^{N_T} \frac{1+k_s^4}{k_s^2-\lambda} \beta_{01} Q_s \beta_{10}}{iK_+ + \sum_s \frac{1+k_s^4}{k_s^2-\lambda} \beta_{01} Q_s \beta_{10}}, \quad (46)$$

, which coincides with the essential Scattering matrix if and only if the corresponding Krein \mathcal{N} -function

$$\sum_{s=1}^{N_T} \frac{1+k_s^4}{k_s^2-\lambda} \beta_{01} Q_s \beta_{10} \quad (47)$$

coincides with the essential part \mathcal{DN}_T^Λ of the DN -map of the intermediate operator - the finite sum of polar terms

$$\sum_{s=1}^{N_T} \frac{P_+ \frac{\partial \varphi_s}{\partial n} \langle P_+ \frac{\partial \varphi_s}{\partial n} |}{\lambda_s - \lambda}. \quad (48)$$

Summarizing above results we obtain the following conditional statement for the extension constructed based on the boundary condition (43) in case when $N_i \cap N_{-i} = 0$ or $\dim E_A = 1$:

Theorem V.1 *The constructed operator \mathbf{A}_β is a solvable model of the Quantum network on the essential interval of energy if and only if the dimension of the space E_A coincides with the number of eigenvalues on the essential interval of energy, the eigenvalues k_s^2 of the operator $A = \sum_{s=1}^{N_T} k_s^2 e_s \langle e_s |$, with some ortho-normal basis e_s , coincide with eigenvalues of the intermediate operator on essential interval of energy and there exist a subspace $N_i = N$ and operator $\beta_{01} : N_i \rightarrow E_+$ such that for that ortho-normal basis $\{e_s\}_{s=1}^{N_T}$ in E_A*

$$P_+ \frac{\partial \varphi_s}{\partial n} = \beta_{01} P_i e_s \quad (49)$$

for all s , $s = 1, 2, 3, \dots, N_T$.

In case when only one resonance eigen-value k_0^2 of the intermediate operator sits on the essential spectral band the obtained model Scattering matrix

$$\mathbf{S}(p) = \frac{iK_+ - \frac{1+k_0^4}{k_0^2-\lambda} \beta_{01} Q_0 \beta_{10}}{iK_+ + \frac{1+k_0^4}{k_0^2-\lambda} \beta_{01} Q_0 \beta_{10}} \quad (50)$$

is a one-pole approximation of the Scattering matrix of the network. The condition of the above theorem are obviously fulfilled for one-pole approximation, when $P_+ \frac{\partial \varphi_0}{\partial n} \neq 0$, $d = 1$, $N_T = 1$, and β_0 is one-dimensional operator mapping the one-dimensional subspace N_i onto the resonance entrance subspace in E_+ spanned by $P_+ \frac{\partial \varphi_0}{\partial n}$. For thin or shrinking

networks one can estimate the deviation of the one-pole approximation from the exact Scattering matrix on the network based on material of section 3. It will be done elsewhere.

Note that there exist an intrinsic connection between the matrix model of the network we propose and method of derivation of the asymptotic of different series of eigenfunctions of Laplace operator on a composite domain with shrinking channels : both are actually based on a shape of eigenfunctions in limiting domain. We hope to develop a comparative analysis of both problems in a forthcoming publication.

The above one-pole approximation has also another important role in perturbation theory: as a sort of a “jump-start” in analytic perturbation procedure. This role may be clarified by the following observation. Consider a simplest network with only one semi-infinite wire and the Fermi level sitting on the first spectral band multiplicity 1. Then the component of the corresponding solvable model in the open channel is presented by the Schrödinger equation

$$-u'' = \lambda u := p^2 u, \quad 0 < x < \infty,$$

with one-dimensional entrance subspace E_+ . Construct the solvable model \mathbf{A}_β of the network assuming that the “inner Hamiltonian” A in course of construction of the solvable model is restricted to a symmetric operator with one-dimensional deficiency subspace $N_i := N$ spanned by the vector e , and $\beta_{01} := \beta$ is the map of N onto E_+ . Then the model Scattering matrix is scalar :

$$\mathbf{S}_\beta(p) = \frac{ip - \beta^2 \sum_s \frac{1+k_s^4}{k_s^2 - p^2} Q_s}{ip + \beta^2 \sum_s \frac{1+k_s^4}{k_s^2 - p^2} Q_s} \quad (51)$$

with $Q_s = |\langle e, e_s \rangle|^2$. Zeroes $k_s(\beta)$ of the Scattering matrix (51) - resonances - sit in upper half-plane and approach the points $\pm k_s$, $k_{-s} = -k_s$, when $\beta \rightarrow 0$. They can be found approximately in form of branching continuous fractions, see [96] as solutions of a chain of algebraic equations. For instance the resonance $p_0 = k_0(\beta)$ created from the eigenvalue k_0^2 of the operator A (more precise : from the point $+k_0$) can be obtained as a solution $p = k_0(\beta)$ of the equation

$$p = k_0 - \frac{\beta^2(1+k_0^4)Q_0}{(p+k_0) \left(ip - \beta^2 \sum_{s \neq 0} \frac{1+k_s^4}{k_s^2 - p^2} Q_s \right)}. \quad (52)$$

Another resonance created at the point $-k_0$ from the eigenvalue k_0^2 sits at the symmetric point $-\bar{k}_0(\beta)$ with respect to the imaginary axis. Other resonances $k_s(\beta)$ can be found from similar equations with $\pm k_0$ substituted by $\pm k_s$. All functions $k_s(\beta)$ are analytic functions of β , k in small neighborhoods of $(0, \pm k_s)$. They sit in the upper half-plane symmetrically with respect to the imaginary axis $k_{-s}(\beta) = -\bar{k}_s(\beta)$. The Scattering matrix (51) is unitary on the real axis k and has poles at the complex-conjugate points $\bar{k}_s(\beta)$ in the lower half-plane , hence it is presented by the finite Blaschke product which tends to 1 when $|k| \rightarrow \infty$:

$$\mathbf{S}^\beta(p) = \prod_s \frac{p - k_s(\beta)}{p - \bar{k}_s(\beta)}. \quad (53)$$

The outer component of the scattered wave is presented as

$$\Psi_0^\beta = e^{-ipx} + \mathbf{S}^\beta(k) e^{-ipx},$$

and fulfills proper boundary condition at the place of contact with the model quantum dot.

Though the resonances depend analytically of (β, p) , neither Scattering matrix (51) nor the Scattered wave depend analytically of (β, p) on the product (U_β, C_p) of a small neighborhood of the origin in β - plane and the whole p -plane. The analyticity is lost due to presence of points $\pm k_s$ where the resonances are created at the origin of the β -plane. But it is present for “separated” factors of the Scattering Matrix. Consider for small β two non intersecting subsets K_0 and K^0 of the set $K = \{k_s\}$ and the corresponding factors \mathbf{S}_0^β , \mathbf{S}_β^0 of the Scattering matrix with resonances created in K_0 , K^0 respectively:

$$\mathbf{S}_0^\beta(p) = \prod_{k_s \in K_0} \frac{p - k_s}{p - \bar{k}_s}, \quad \mathbf{S}_\beta^0(p) = \prod_{k_s \in K^0} \frac{p - k_s}{p - \bar{k}_s}.$$

Here the first factor is an analytic function of (β, p) when β is small and p sits near K^0 , and, vice versa, the second factor is analytic for small β and p sits in a small neighborhood of K_0 . In particular the first factor can be expand into Taylor series in (β, p) for small $\beta \in U_\beta$ if p sits in some small neighborhood U^0 of K^0 , and the second factor is presented by the Taylor series in (β, p) if $\beta \in U_\beta$ and p sits in a small neighborhood U_0 of K_0 . On the other hand, the first factor is not an analytic function of (β, p) if $\beta \in U_\beta$ and p is near to K_0 . This observation may be interpreted as a fact of the perturbation theory the following way.

Assume that $k_0 > 0$ and consider the representation of the Scattering matrix (53) in form of product of two factors : the product containing the resonances $k_0(\beta)$, $-\bar{k}_0(\beta)$ created from the eigenvalue k_0^2

$$\mathbf{S}_0^\beta(p) = \frac{[p - k_0(\beta)] [p + \bar{k}_0(\beta)]}{[p - \bar{k}_0(\beta)] [p + k_0(\beta)]},$$

and the complementary factor \mathbf{S}_β^0

$$\mathbf{S}_\beta^0(p) = \prod_{s \neq 0} \frac{p - k_s(\beta)}{p - \bar{k}_s(\beta)}.$$

One can derive from the above dispersion equation (52) that the resonances are analytic functions of the perturbation parameter β near the origin $\beta = 0$, but the factor $\mathbf{S}_0^\beta(p)$ is not for the reason discussed above.

Theorem V.2 *There exist a one-dimensional perturbation \mathcal{L}_0^β of the operator*

$$l_0 u = -u'', \quad u \Big|_0 = 0$$

with a non-trivial inner component, such that the scattering matrix of the pair $(\mathcal{L}_0^\beta, l_0)$ coincides with $-\mathbf{S}_0^\beta(p)$. Then the Scattering matrix \mathbf{S} of the complementary pair $(\mathcal{L}_0^\beta, \mathcal{L}^\beta)$ is equal to the complementary factor $-\mathbf{S}_\beta^0(p)$:

$$\mathbf{S}_\beta(p) = \mathbf{S}_0^\beta(p) \mathbf{S}_\beta^0(p).$$

The complementary factor is an analytic function of (β, k) on the product of a small neighborhood of the origin in β -plane and a small neighborhood K_0 of $(k_0, -k_0)$ in p -plane.

Proof Consider the one-dimensional operator A with a positive eigenvalue κ^2 . We associate with it the Krein function $\mathcal{M} = \frac{1-\kappa^2}{\kappa^2-\lambda}$. Then restrict the operator l_0 onto smooth functions vanishing at the origin $x = 0$, and construct the self-adjoint extension \mathbf{A}_0^β defined by the hermitian matrix $\{\beta\}$ which connects the boundary values ξ_+ , $-\mathcal{M}\xi_+$ in E_A with boundary values $\Psi(0)$, $\Psi'(0)$ in E_+ :

$$\begin{pmatrix} \Psi' \\ -\xi_+ \end{pmatrix} = \begin{pmatrix} \beta_{00} & \beta_{01} \\ \beta_{10} & \beta_{11} \end{pmatrix} \begin{pmatrix} \Psi \\ -\xi_- \end{pmatrix}. \quad (54)$$

Substituting into the above equation the corresponding Ansatz for the wave-function in the outer space

$$\Psi_0^\beta(x, p) = e^{-ipx} + \mathbf{S}^\beta(p)e^{-ipx},$$

we obtain an explicit expression for the corresponding Scattering matrix \mathbf{S} in terms of the inner Krein-function $\mathcal{M}(\lambda) = \frac{1+\kappa^4}{\kappa^2-\lambda}$ and the boundary parameters:

$$\mathbf{S}(\lambda) = \frac{ip + \left[\beta_{00} - \frac{|\beta_{01}|^2 \mathcal{M}}{1+\beta_{11} \mathcal{M}} \right]}{ip - \left[\beta_{00} - \frac{|\beta_{01}|^2 \mathcal{M}}{1+\beta_{11} \mathcal{M}} \right]}.$$

Select the parameter β_{11} such that $1 - \beta_{11} \kappa^2 = 0$, then $1 + \beta_{11} \mathcal{M} = \beta_{11} \frac{1+\kappa^4}{\kappa^2-\lambda}$, and the Scattering matrix takes the form with $\lambda = p^2$

$$\mathbf{S}(\lambda) = \frac{ip + \beta_{00} - \frac{|\beta_{01}|^2}{\beta_{11}(1+\kappa^4)} - \frac{|\beta_{01}|^2 \kappa^2}{(1+\kappa^4)\beta_{11}} p^2}{ip - \beta_{00} + \frac{|\beta_{01}|^2}{\beta_{11}(1+\kappa^4)} + \frac{|\beta_{01}|^2 \kappa^2}{(1+\kappa^4)\beta_{11}} p^2}.$$

Comparing this expression with

$$\begin{aligned} -\mathbf{S}_0^\beta(p) &= -\frac{[(p - k_0(\beta))][p + \bar{k}_0(\beta)]}{[p - \bar{k}_0(\beta)][p + k_0(\beta)]} = \\ &= \frac{-p^2 + 2i\Im k_0(\beta)p + |k_0(\beta)|^2}{p^2 - 2i\Im k_0(\beta)p - |k_0(\beta)|^2} = \mathbf{S}(\lambda), \end{aligned}$$

we obtain the equations for selection of parameters of the extension \mathbf{A}_0^β :

$$\frac{\beta_{00} - \frac{|\beta_{01}|^2}{\beta_{11}(1+\kappa^4)}}{|k_0(\beta)|^2} = \frac{1}{2\Im k_0(\beta)} = \frac{|\beta_{01}|^2 \kappa^2}{(1+\kappa^4)\beta_{11}}. \quad (55)$$

Solution is not unique, but may be parametrized by the functional parameter β_{00} :

$$\kappa^2 = \frac{1}{2\beta_{00}\Im k_0(\beta) - |k_0(\beta)|^2}.$$

In particular we may choose: $\beta_{00} = |k_0(\beta)|^2 (\Im k_0(\beta))^{-1}$. Then

$$\kappa^2 = \frac{1}{|k_0(\beta)|^2}.$$

To finalize the calculation we notice that both $|k_0(\beta)|^2$ and $\Im k_0(\beta)$ are real analytic functions of β , hence κ^2 is an analytic function of β . The boundary parameter β_{00} has a pole at the origin since $k_0(\beta) \rightarrow k_0(0) = \bar{k}_0(0)$ when $\beta \rightarrow 0$. Other boundary parameters may be also chosen based on above equations (55) as $\beta_{11} = |k_0|^2$, $|\beta_{01}|^2 = \frac{4+|k_0|^4}{4\Im k_0}$. Alternative choice is $\kappa^2 = |k_0|^2$, $\beta_{00} = \frac{1+|k_0|^4}{2\Im k_0 |k_0|^2}$, $|\beta_{01}|^2 = \frac{1+|k_0|^4}{2\Im k_0 |k_0|^4}$, $\beta_{11} = |k_0|^{-2}$, with $k_0 := k_0(\beta)$. This accomplishes the construction of the operator \mathbf{A}_0^β .

The operator \mathbf{A}_0^β permits to make a sort of a “jump-start” in perturbation procedure for the pair of operators $\{(l \oplus H), \mathbf{A}_\beta\}$: the scattering matrix $\mathbf{S}_0^\beta(k)$ for the pair $\{(l \oplus H), \mathbf{A}_0^\beta\}$ is calculated in explicit form, and the complementary scattering matrix for the pair $\{\mathbf{A}_0^\beta, \mathbf{A}_\beta\}$, which coincides with \mathbf{S}_β^0 , is an analytic function of (β, p) near to the resonance k_0 and can be calculated via standard analytical perturbation procedure.

Though the “jump-start” can help to develop the analytic perturbation procedure, according to the preceding result, but exact calculation of the pole $k_0(\beta)$ and corresponding projection for the perturbed operator \mathbf{A}_β , which were used in course of construction of the “jump-start”, may be a tricky analytical problem, comparable with the original spectral problem. On the other hand, the asymptotic expansion for these data for small β may be useful for obtaining estimates, but does not help to derive analyticity of the complementary factor of the Scattering matrix constructed for the corresponding approximate “jump start” factor, constructed based on approximate asymptotic data.

VI. CONCLUSION: INTERMEDIATE OPERATOR IN ANALYTIC PERTURBATION TECHNIQUES

Classical analytic perturbation techniques, see for instance [46], is developed for additive perturbations of operators with discrete spectrum $A \rightarrow A + \varepsilon B$. For perturbation of the continuous spectrum Kato suggested another techniques based on Wave operators. Detailed study of the perturbation of operators with continuous spectrum in model situations, especially for the Friedrichs model, see [29], was done in numerous mathematical papers and books, see [82] and the references therein and also [30, 31, 41, 71]. It was already clear for specialists long ago, that the classical techniques of the analytic perturbation theory does not work generally on continuous spectrum (actually it works below the threshold of creation of resonances, see [29]). Probably I. Prigogine alone insisted on modification of the analytic perturbation techniques to cover the case of continuous spectrum.

According to evidence from long-time Prigogine’s collaborator Professor I. Antoniou, I. Prigogine attempted also to use the idea of an *intermediate operator* as a base for development of the analytic perturbation techniques for operators with continuous spectrum. He

tried to construct the intermediate operator A_1 as a function of the non-perturbed operator A with a hope that after the first step $A \rightarrow A_1$ the analytical perturbation procedure for the perturbed operator $A + \varepsilon V$ presented as $A_1 + \varepsilon V'$ becomes convergent. This simplest suggestion appeared to be not so efficient as expected, and Prigogine abandoned this idea finally, see [5, 76, 77, 78, 79, 80]

Note that actually the idea of the intermediate operator in another context appeared in *Splitting Method* invented by I. Glazman, see [35]. This method radically transformed in seventies the whole picture of the qualitative spectral analysis of singular differential operators, but was never used in context of the analytic perturbation procedure.

We actually suggested revisiting the idea of the intermediate operator again in a special case of quantum networks where the candidate for the role of an intermediate operator is almost obvious. In our case it is not a function of the non-perturbed operators, but *is obtained from it just by a finite-dimensional perturbation*. Actually we succeeded to apply the splitting method to Quantum Networks because of the step-wise structure of the continuous spectrum in wave-guides. This minor change of the original idea of Prigogine appears to be useful for perturbation problems in wave-guides. In our case the idea of the intermediate operator is automatically combined with resonances, which was anticipated long ago by Poincare and intensely discussed by Prigogine with references to Poincare, see [74, 79].

The only essential, and even decisive difference of our version of the intermediate operator from the version which I. Prigogine attempted to use, is the natural principle of *spectral locality* we impose: we construct the intermediate operator and the scattered waves via the special perturbation procedure *locally* - in a certain spectral interval, - but not globally, as Prigogine planned. It is quite easy to define this interval mathematically for the Quantum Networks: it is the maximal interval containing the Fermi level, [60], where the spectral multiplicity n is constant and the scattering matrix is a square matrix size $n \times n$. This interval may be either a spectral band corresponding to some channel in one of semi-infinite wires, of a sum of several spectral bands (sort of a "spectral terrace") corresponding to different wires, with properly hybridized scattered waves. The structure of the corresponding scattered waves within this spectral interval is manifested by the structure of the scattering matrix and corresponds to the n -dimensional input-output. The structure of scattered waves on the neighboring spectral bands is different.

It is worth to notice, that slightly modified procedure permits to construct an hierarchy of intermediate operators also for some operators with absolutely-continuous spectrum of constant multiplicity, in particular for Friedrichs model.

In actual paper we discussed simplest wave-guiding systems composed of straight wave-guides (quantum wires). The convenience of this trivial environment appears from existence of explicit formulae for oscillatory modes in straight wave-guides: the system of thresholds and the structure of the entrance sub-spaces in this environment is trivial. Study of more interesting systems of periodic or asymptotically straight wave-guides with rapidly decreasing curvature requires a combination of our methods with Lippmann-Schwinger techniques developed in case of wave-guides with non-trivial geometry for discrete and especially for continuous spectrum, see [19, 21, 37, 49, 50, 51].

On the other hand, the suggestion to recover resonances from the discrete spectrum of some intermediate operator can be easily applied to any wave-guiding problem in trivial

environment, with linear vertices, on a reasonable price of preliminary study of the “intermediate” dynamics. In particular, it permits to suggest alternative approach to study of trapped modes in acoustics and hydro-dynamics, investigated in [18, 25], as well as to classical theory of electro-magnetic wave-guides with local variation of curvature, [20]. An important advantage of our techniques is: the possibility of “fitting” of the constructed “solvable model” based of results of straightforward computing for the intermediate problem.

VII. ACKNOWLEDGEMENT

Two of co-authors (A.M and B.P) acknowledge support from the Russian Academy of Sciences, Grant RFBR 03-01- 00090 and from research allocation of the University of Auckland. All authors are grateful to Doctors M. Harmer, V. Olejnik and V. Kruglov for interesting comments on the text and to Dr. R. Shterenberg for extended discussion of questions concerning the singular spectrum in channels, important references and materials [44] supplied. The authors are grateful to Professor I. Antoniou for inspiring information on Prigogine’s experience in analytic perturbation theory and interesting materials supplied.

BP is grateful to Professor L. Faddeev for an extended discussion of the perturbation of the continuous spectrum for the Friedrichs model, which clarified the structure of the hierarchy of intermediate operators.

-
- [1] V. Adamyan. *Scattering matrices for microschemas*. Operator Theory: Adv. and Appl. **59** (1992) pp 1-10.
 - [2] V.M.Adamyan,B.S.Pavlov *Zero- radius potentials and M.G.Krein’s formula for generalized resolvents* , Zap. Nauch. Sem. Leningrad. Otdel. Mat. Inst. Steklov. (LOMI), **149** (1986), Issled. Linein. Teor. Functsii. XV, 7-23, 186.
 - [3] J. del Alamo, C. Eugster *Quantum field-effect directional coupler* Appl. Phys. Letters **56** (1), January 1, 1990, pp 78-83.
 - [4] S. Albeverio, F. Gesztesy, R. Hoegh-Krohn, H. Holden, *Solvable models in quantum mechanics*. Springer-Verlag, New York,1988.
 - [5] I. Antoniou, S. Tasaki Generalized Spectral Decompositions of Mixing Dynamical Systems IN: International Journal of Quantum Chemistry,**40** (1993), pp 425-474.
 - [6] S.Albeverio, P.Kurasov *Singular Perturbations of Differential Operators*, London Math. Society Lecture Note Series 271. Cambridge University Press 2000, 429 p.

- [7] N.T. Bagraev, V.K. Ivanov, L.E. Kljachkin, A.M. Maljarenko, S.A. Rykov, I.A. Shelyh *Interference of charge carriers in one-dimensional semiconductor rings*. Physics and techniques of semiconductors, v34 (2000) p 7.
- [8] N.T. Bagraev, V.K. Ivanov, L.E. Kljachkin, A.M. Malyarenko, I.A. Shelych. *Ballistic Conductance of a Quantum Wire at finite Temperatures* Semiconductors , **34**, 6 (2000) p 712-716.
- [9] N.T.Bagraev, A.B.Mikhailova, B.S.Pavlov, L.V. Prokhorov, A.M.Yafyasov *Temperature stability of the triadic resonance quantum switch*,10-th MEL-ARI/NID Workshop, Helsinki,1-3 July 2002 Academy of Finland.
- [10] N.Bagraev,A.Mikhailova,B. Pavlov,L.Prokhorov, A.Yafyasov *Resonance Quantum Switch: search of working parameters*. Submitted to Phys.Rev. B.
- [11] N. Bagraev,B.Pavlov, A.Yafyasov *Resonance Quantum Switch: search of working parameters*In: Internacional Conference on Simulation of Semiconductor Processes and Devices: SIS-PAD 2003, (Boston 3-5 Sept.2003),pp 275-278
- [12] C.W.J.Beenakker, H. van Houten. *Quantum transport in semiconductor nanostructures*. In: H.Ehrenreich, D.Turnbull (Eds.) *Solid State Physics. Advances in Research and Applications*. **44** (1991). Academic Press, San Diego. p. 1-228.
- [13] F.A.Berezin, L.D. Faddeev *A remark on Schrödinger equation with a singular potential* Soviet Math. Dokl. **2** (1961) pp 372-376
- [14] V. Bogevolnov, A, Mikhailova, B. Pavlov, A. Yafyasov *About Scattering on the Ring* In: "Operator Theory : Advances and Applications", Vol 124 (Israel Gohberg Anniversary Volume), Ed. A. Dijksma, A.M. Kashoek, A.C.M.Ran, Birkhäuser, Basel 2001,pp 155-187.
- [15] M.Büttiker, A.Pretre, H.Thomas *Dynamic conductance and the scattering Matrix of Small Conductors* Phys. Rev. Lett. **70** (1993) pp 4114-4117
- [16] M.Büttiker,Y.Imry,R.Landauer,S.Pinhas, *Generalized many-channel conductance formula with application to small rings* Phys.Rew.B **31** (1985), pp 6207-6215
- [17] R.Carlson *Adjoint and self-adjoint differential operators on graphs* Electron. J. Differential Equations 1998, No. 6, 10 pp. (electronic).
- [18] E.B. Davies and L. Parnowski *Trapped modes in acoustic waveguides* Quart. Journal Mech. ASppl. Math. **51** (1998) pp 477-492
- [19] Y.Dermenjian, M. Durand, and V. Iftimie *Spectral analysis of an acoustic multistratified perturbed cylinder* Commun. in Partial Differential Equations **23**, 1&2, (1998) pp 141-169

- [20] P.Duclos, P. Exner and P. Stovicek Curvature-induced resonances in two-dimensional Dirichlet tube Ann. Inst. H. Poincare **62** (1995), pp 81-101
- [21] P.Duclos, P. Exner, D. Krejcirik *Bound states in curved quantum layers* Commun. Math. Physics **223** (2001) pp 13-28
- [22] European Comission IST programme: Future and emerging Technologies. *Technology Roadmap for Nanoelectronics*, R. Compano (ed.), Second edition, Nov. 2000. Luxemburg: Office for Official Publications of the European Communities. 105 p.
- [23] M.S.P. Eastham, H. Kalf *Schrödinger type operators with continuous spectra* Research Notes in Mathematics, **65** Pitman (Advanced Publishing Program), Boston, Mass.- London (1982) 281 pp.
- [24] J.Edward *Eigenfunction decay and eigenvalues accumulation for the laplacian on asymptotically perturbed waveguides* In: Journal of London Mathematical Society,**59**, 2 (1999), pp 177-182
- [25] D.Evans, L. Levitin and D. Vassiliev *Existence theorems for trapped modes* Journ. Fluid Mech. **261** (1994) pp 21-31
- [26] P. Exner, K. Nemcova *Leaky Quantum Graphs: approximation by Point Interaction Hamiltonians* J. Phys. A, **36** (2003) 10173 - 10193
- [27] P. Exner, P. Šeba. *A new type of quantum interference transistor*. Phys. Lett. A 129:8,9 (1988) pp 477-480.
- [28] P. Exner, P. Šeba ,M.Tater *Bound states and Scattering in quantum waveguides coupled laterally through a boundary window* Journal of Mathematical Physics, **37** (1996), 10 , pp 4467-4887.
- [29] K.O.Friedrichs *On the perturbation of continuous spectra* Communications in Pure and Applied Mathematics **1** (1948) pp 361-406.
- [30] L.Faddeev *On a model of Friedrichs in the theory of perturbations of the continuous spectrum* Trudy Mat. Inst. Steklov **73** (1964) pp 292-313.
- [31] L.Faddeev,B.Pavlov *Zero-sets of operator-functions with a positive imaginary part* In: Linear and Complex Analysis Problems (199 Research Problems) Lecture Notes in Mathematics 1043, ed. V. Havin, S. Hrushev, N. Nikolskii (1984) pp 124-128.
- [32] M. Faddeev, B. Pavlov. *Scattering by resonator with the small opening*. Proc. LOMI, v126 (1983). (English Translation J. of Sov. Math. v27 (1984) pp 2527-2533)

- [33] N.I. Gerasimenko and B.S. Pavlov. Scattering problems on compact graphs. Theor. Math. Phys. 74, 230 (1988).
- [34] Y.Ginzburg *Multiplicative representations and minorants of bounded analytic operator-functions* In: Functional Analysis and it's Applications, **1:3** (1967),pp 9-23
- [35] I. Glazman *Direct methods of qualitative spectral analysis of singular differential operators* Translated from the Russian by the IPST staff (Israel Program for Scientific Translations), Jerusalem, 1965; Daniel Davey & Co., Inc., New York 1966 , 234 p.
- [36] I.S. Gohberg and E.I. Sigal. Operator extension of the theorem about logarithmic residue and Rouchet theorem. Mat. Sbornik. 84 (1971) p 607.
- [37] J. Goldstone and R.L. Jaffe *Bound states in twisting tubes* Phys. Rev. B **45** (1992) 14100-14107
- [38] V.I.Gorbachuk *Boundary problems for differential- operator equations* (in Russian) Kiev, Naukova Dumka (1984) 284 p
- [39] M. Harmer *The matrix Schrdinger operator and the Schrdinger operator on graphs* PhD thesis, Auckland University, 2000.
- [40] M. Harmer Inverse scattering for the matrix Schrdinger operator and Schrdinger operator on graphs with general self-adjoint boundary conditions ANZIAM Journal, 43 (2002), 1-8.
- [41] J.Howland. *Finite rank perturbations of singular spectra* Proc. Amer. Math. Soc. **97** (1986), no. 4, pp 634–636.
- [42] H.Ishio,K.Nakamura *Quantum Transport in Open Billiards: Dependence on Degree of Opening* J.Phys. Society Japan **61** (1992) pp 2649-2651
- [43] S. Jimbo *Perturbation formula of eigenvalues in a singularly perturbed domain* J. Math. Soc. Japan **45**, 2 (1993), pp 340-356
- [44] V. Kalvin, P. Nejtaanmjaki,B.Plamenevskij *On accumulations of the discrete spectrum of elliptic boundary problems in domains with cylindrical tails.* Manuscript.
- [45] H. Kasai,K. Mitsutake, A. Okiji *Effects of Confining Geometry on Ballistic Transport in Quantum Wires* J.Phys. Society Japan**60** (1991) pp 1679-1688
- [46] T. Kato *Perturbation theory for linear operators* Springer Verlag, Berlin-Heidelberg-NY, Second edition, 740 pp.
- [47] V.Kondratjev, E.Landis *Qualitative theory of second order linear partial differential equations* in: Partial adifferential Equations 3, ITOGI NAUKI SSSR, VINITI, Moscow (1988) pp 99-215.
- [48] A.Silbergleit, Yu. Kopilevich *Spectral theory of guided waves.* Institute of Physics publishing,

- Bristol (1996), 310 p.
- [49] D. Krejcirik *Quantum strips of surfaces* J. Geom. Phys. **45**, 1-2 (2003) pp 203-217
 - [50] D. Krejcirik and J. Kriz *On the spectrum of curved Quantum Waveguides* arXiv:math-ph/0306008 v1 3 June 2003, 34 p.
 - [51] David Krejcirik and Rafael Tiedra de Aldecoa *The nature of the essential spectrum in curved quantum waveguides* arXiv: math-ph/ 0307019 v1 9 July 2003, 20 p.
 - [52] V. Kostykin and R. Schrader. *Kirchhoff's rule for quantum wires*. J. Phys. A: Math. Gen. v32 (1999) pp 595-630.
 - [53] M.A.Krasnosel'skij *On selfadjoint extensions of Hermitian Operators*(in Russian) Ukrainskij Mat.Journal **1**(1949) pp 21-38
 - [54] M.Krein *Concerning the resolvents of an Hermitian operator with deficiency index (m,m)* ,Doklady AN USSR ,**52** (1946) pp 651-654.
 - [55] P. Kuchment, H. Zengh *Convergence of spectra of mesoscopic systems collapsing onto graph* Journal Math. Anal. Appl. **258** (2001), pp 671-700
 - [56] P. Kuchment *Graph models for waves in thin structures* Waves in Periodic and Random Media, **12** (2002) pp 1-24.
 - [57] P. Kurasov, B. Pavlov, *Operator relation and Scattering matrix* In: Operator Theory: Advances and Applications, **113**, ed. Nikolskij and all, *Complex Analysis, Operators and Related Topics, S.A. Vinogradov - in memoriam*, Birkhauser Verlag, Basel,2000, pp 294-305.
 - [58] R.Landauer *Electrical Resistance of Disordered One-dimensional Lattices* Phil. Mag. **21**(1970) pp 863-867
 - [59] P. Lax, R. Phillips *Scattering theory* Academic press, New York, 1967.
 - [60] O. Madelung. *Introduction to solid-state theory*. Translated from German by B. C. Taylor. Springer Series in Solid-State Sciences, 2. Springer-Verlag, Berlin, New York, 1978. 486 p.
 - [61] V. M. Maz'ja. *Sobolev Spaces*, Translated from the Russian by T. O. Shaposhnikova. Springer Series in Soviet Mathematics. Springer-Verlag, Berlin (1985).
 - [62] A. Mikhailova, B. Pavlov, I. Popov, T. Rudakova, A. Yafyasov *Scattering on Compact Domain with Few Semi-Infinite Wires Attached: resonance case* In: " Mathematische Nachrichten", **235**,1 (2002) ,pp 101 -128.
 - [63] A.Mikhailova, B. Pavlov *Quantum Domain as a triadic Relay* In: Unconventional models of Computations UMC'2K, ed. I. Antoniou, C. Calude, M.J. Dinneen, Springer Verlag series

- for Discrete Mathematics and Theoretical Computer Science (2001) pp 167-186
- [64] A.Mikhailova, B. Pavlov, L. Prokhorov *Modelling of Quantum Networks*, Department of Mathematics of the University of Auckland report series, 508, October 2003, 49 p.
 - [65] M.Naimark *Self-adjoint extensions of the second kind of a symmetric operator*, Bull.AN USSR, Ser.Math.4 (1946), pp 53-104.
 - [66] S.P. Novikov. *Schrödinger operators on graphs and symplectic geometry*, in: The Arnol'dfest (Proceedings of the Fields Institute Conference in Honour of the 60th Birthday of Vladimir I. Arnol'd), eds. E. Bierstone, B. Khesin, A. Khovanskii, and J. Marsden, Fields Institute Communications Series, 1999.
 - [67] T.Palm, L.Thylen *Analysis of an electron-wave Y-branch switch* Applied Phys. Letters **60** (1992) pp 237-239
 - [68] B.Pavlov. *S-Matrix and Dirichlet-to-Neumann Operators* In: *Scattering* (Encyclopedia of Scattering), ed. R. Pike, P. Sabatier, Academic Press, Harcourt Science and Tech. Company (2001) pp 1678-1688
 - [69] B.Pavlov *Resonance Quantum Switch: matching domains* In: *Surveys in Analysis and Operator Theory*.Proc. of the Center of Math. and Appl. ANU **40** Nov. 2002, pp 127-156
 - [70] B. Pavlov. *The theory of extensions and explicitly solvable models* (In Russian) Uspekhi Mat. Nauk, **42** (1987) pp 99–131.
 - [71] B.Pavlov, S.Petras *The singular spectrum of a weakly perturbed multiplication operator* In: Funkcional. Anal. i Priložen.(Russian) **4** no. 2, (1970) pp 54–61.
 - [72] B. Pavlov *A model of zero-range potential with an internal structure*(in Russian) Teor. Mat. Fizika,**59** (1984), pp 345-353 (English Translation : Theor. and Math. Physics **59** (1984) pp 544-550)
 - [73] L. Parnowski *Spectral asymptotics of the Laplace operator on manifolds with cylindrical ends* In : Intern. Journ. Mathematics **6** (1995) pp 911-920
 - [74] H. Poincare *Methodes nouvelles de la mecanique celeste* Vol. 1 (1892), Dover, New York (1957)
 - [75] V.Potapov *Factorization of analytic matrix-function* (In Russian) Trudy Moskovskogo Matematicheskogo obshchestva, 1952.
 - [76] I. Prigogine, C. George, L. Rosenfeld *A Unified Formulation of Dynamics and Thermodynamics* In: *Chemica Scripta* **4** (1973), pp 5-32.

- [77] I. Prigogine *Irreversibility as a Symmetry-breaking Process* In : Nature, **246**, 9 , November 1973.
- [78] C. George, F. Mayne and I. Prigogine *Scattering Theory in Superspace* In: Advances in Chemical Physics, **61**, Ed. John Wiley & Sons, Inc., (1985) pp 223-299.
- [79] I. Prigogine The microscopic meaning of Irreversibility In: Zeitschrift für phys. Chemie, **270**, 3, Leipzig (1989) pp 477-490.
- [80] I. Prigogine *Why Irreversibility? The formulation of Classical and Quantum Mechanics for nonintegrable systems* International Journal of Quantum Chemistry, **53** (1995), p 105-118.
- [81] L.E. Reichl *The transition to Chaos in conservative Classical Systems: Quantum Manifestations* Springer-Verlag, NY, 1992. 551 p
- [82] J. Reed, B. Simon *Methods of modern Mathematical Physics* V.1-5, Academic press, New-York, 1979.
- [83] J. Rubinstein, M. Shatzman *Variational approach on multiply connected thin strips I : Basic estimates and convergence of the Laplacian spectrum* Arch. Ration. Mech. Analysis **160**, 4 (2001), pp 271-308
- [84] F. Rellich *Das Eigenwertproblem von $\Delta u + \lambda u = 0$ in Halbrohren* in: Studies and Essays presented to R. Courant on his 60 Birthday, January 8, 1948, Interscience Publishers, Inc., New-York (1948) pp 329-344.
- [85] I. Safi *A dynamic scattering approach for a gated interacting wire* The European Physical Journal B **12** (1999), pp 451-455
- [86] M. Schatzman *On the eigenvalues of the Laplace operator on a thin set with Neumann boundary conditions* Applicable Anal. **61** (1996) pp 293-306
- [87] J. Sirokov *Strongly singular potentials in one-dimensional Quantum Mechanics* Teor. Mat. Fiz. **41** 3 (1979) pp 45-49
- [88] J. Sirokov *Strongly singular potentials in three-dimensional Quantum Mechanics* Teor. Mat. Fiz. **42** 1 (1980) pp 291-302
- [89] A. Sobolev, M. Solomyak, *Schrödinger operators on homogeneous metric trees: spectrum in gaps.* Rev. Math. Phys. **14** no. 5 (2002), pp 421-467.
- [90] J. Sylvester, G. Uhlmann *The Dirichlet to Neumann map and applications.* In: Proceedings of the Conference “Inverse problems in partial differential equations (Arcata, 1989)”, SIAM, Philadelphia, 1990, pp 101-139.

- [91] C.Thelander,M.Magnusson,K.Deppert,L.Samuelson *Gold nanoparticles single-electron transistor with carbon nanotubes* Applied Physics letters **79** 13 (2001) pp 2106-2108
- [92] E.C.Titchmarsh, *Eigenfunctions expansions associated with second order differential equations*, Clarendon Press, Oxford (1962), Vol. 1, 203 p
- [93] W.G.Van der Wiel, Yu.V. Nazarov, S. De Franceschi, T. Fujisawa, J.W. Elzerman, E.W.G.Huizeling, S.Tarucha and L.P. Kouwenhoven *Electro-magnetic Aharonov-Bohm effect in a @-D electron gas ring* Phys. Rev. B, November 2002.
- [94] H.Q.Xu *Electrical properties of three-terminal ballistic junction* Applied Phys. Letters **78**14 (2001), pp 2064-2066
- [95] H.Q.Xu *Diode and transistor behaviour of three-terminal ballistic junctions* Applied Phys. Letters **80** (2002) pp 853-858
- [96] V. Voevodin, Y. Kuznetsov *Matrices and calculations* Nauka, Moscow (1984) (In Russian), 319 p.
- [97] D. Yafaev *Mathematical Scattering Theory: General Theory* Amer. Math. Society: Translations of Mathematical Monographs,**105**, Providence, Rhode Island 342 p.